
**SECTION 24, TOWNSHIP 38, RANGE 12 SECTION 25, TOWNSHIP 38, RANGE 12** 



(CONTROLLER #1, #2 AND #3)

## GENERAL NOTES FOR CONTROL CABINET

- 1. ENTIRE CONTROL CABINET SHALL BE GROUNDED.
- 2. ALL WIRING SHALL BE TAGGED WITH SELF-STICKING WIRE MARKERS.
- GROUND BUS TO BE COLOR CODED GREEN, NEUTRAL BUS WHITE, AND BONDED TO CABINET. ENCLOSURE, BY LISTED PRESSURE CONNECTORS OR LISTED CLAMPS.
- 4. ALL INTERNAL CONTROLLER WIRING TO BE NO.12 AWG UNLESS OTHERWISE SPECIFIED.
- 5. CABINET WIRING INSULATION TO BE TYPE XHHW OR APPROVED EQUAL.

## LIGHTING GENERAL NOTES


- 1. ALL WORK TO CONFORM TO THE NATIONAL ELECTRICAL CODE AND ANY APPLICABLE LOCAL CODES.
- 2. CONTRACTOR TO VERIFY LOCATION OF ALL UNDERGROUND UTILITIES BEFORE TRENCHING OR AUGERING.
- 3. BEFORE INSTALLING STANDARDS NEAR OVERHEAD FACILITIES CALL C.E. Co. FOR APPROVAL OF LOCATION.
- 4. FOR LOCATION OF EXISTING UNDERGROUND ELECTRICAL CABLE CALL C.E. Co.
- 5. SIZE ALL CONDUIT AS SPECIFIED ON DRAWINGS.
- 6. CONTRACTOR SHALL TAKE ALL NECESSARY MEASURES TO RESTORE ANY SPECIALIZED LANDSCAPING, (i.e. DECORATIVE ROCKS, SHRUBS, PLANTS, ECT.) OR SHALL REPLACE IT, THE COST OF WHICH SHALL BE CONSIDERED INCIDENTAL TO THE CONTRACT.

## CONTROLLER WIRING DIAGRAM LEGEND

- 3-1/C, NO. 2, 600V SERVICE WIRE IN 2" DIA. GALVANIZED STEEL CONDUIT FOR 240/480 VOLT, 1ø, 3 WIRE, 60HZ. SERVICE. 1
- (1) 60 AMP MAIN CIRCUIT BREAKER, 2 POLE, 600 VOLT, 100 AMP BASE, NON-INTERCHANGEABLE TRIP INTERRUPTING RATING NEMA 14000 AMP AT 480 V.
- (1) 60 AMP REMOTE CONTROL CONTACTOR SWITCH, ELECTRICALLY OPERATED, MECHANICALLY HELD, 2 POLE, SINGLE THROW, MINIMUM 60 AMP, 600 VOLT 3
- 4 (4) 30 AMP CIRCUIT BREAKER, 1 POLE, 240 VOLT, 100 AMP BASE, NON-INTER-CHANGEABLE TRIP RATING NEMA - 14000 AMP AT 240 VOLTS.
- (3) 20 AMP CONTROL CIRCUIT—CIRCUIT BREAKER, 1 POLE, 240 VOLT, 100 AMP BASE, NON—INTERCHANGEABLE TRIP INTERRUPTING RATING NEMA 14000 AMP AT 240 V. (5)
- (1) 20 AMP, 1 POLE DOUBLE THROW, 240 VOLT RELAY
- (1) 1.5 KVA, SINGLE PHASE, ENCAPSULATED TRANSFORMER 240x480/120x240 VOLT, 60 HZ. 7
- 8 (1) 20 AMP, 120 VOLT DUPLEX GFCI RECEPTACLE.
- 9 NEUTRAL BUS BAR, 1/4"x1"x12" LONG MOUNTED ON PANEL WITH TAPS.
- 10 3 POSITION SELECTOR SWITCH
- (1) SWITCH FOR LIGHTING FIXTURE MOUNTED IN BOX.
- (12) WEATHER-PROOF INCANDESCENT LIGHTING FIXTURE WITH 60 WATT, 120 V LAMP.
  - PHOTOCELL MOUNTED TO BOTTOM OF VENTED CONTROL CABINET OVERHANG
- (14) NO.8 AWG INSULATED GROUND WIRE
- (15) IN-LINE FUSEHOLDER WITH FUSE AS NOTED IN FUSE TABLE
- (16) GROUND BUS BAR 1/4"x1"x12" LONG MOUNTED ON PANEL WITH TAPS.
- (17)

(13)

- (18) SURGE SUPPRESSOR
- (A) PROPOSED CIRCUIT
- (c) PROPOSED CIRCUIT
- (D) PROPOSED CIRCUIT
- PROPOSED CIRCUIT




SPLICING ELECTRIC CABLES BASIC MATERIALS AND METHODS

COUNTY TOTAL SHEETS SECTION NO. 1537 06-00053-00-LT COOK 009 008 FED. ROAD DIST. NO. ILLINOIS FED. AID PROJECT

CONTRACT #83900

NOMINAL WATTAGE FUSE SIZE 5.0 AMP

LUMINAIRE FUSE SIZE TABLE



## (TYPICAL FOR SINGLE LUMINAIRE INSTALLATION)

ILLINOIS DEPARTMENT OF TRANSPORTATION REVISIONS 71ST STREET DATE STREET LIGHTING **LIGHTING DETAILS** SCALE: VERT, NA HORIZ, NA DATE 02/23/07 DRAWN BY PS CHECKED BY PB