## GENERAL NOTES

- 1. CONTRACTOR TO CONNECT AERIAL CABLE TO EXISTING LIGHTING CONTROLLER AND RUN UP WOOD SUPPORT POLE, EXTEND TO WOOD LIGHT POLES SHOWN TO FEED TEMPORARY STREET LIGHTS FAST AND WEST.
- 2. CONTRACTOR SHALL MAINTAIN POWER TO EXISTING LIGHT POLES DESIGNATED AS 'E' UNTIL COMPLETION OF CONSTRUCTION PHASE I, FROM EXISTING LIGHTING CONTROLLERS UNLESS NOTED OTHERWISE INDICATED ON PLANS.
- 3. CONTRACTOR SHALL DISCONNECT EXISTING CIRCUITS SERVING LIGHT POLES DESIGNATED AS "R" FROM EXISTING CONTROLLER.
- 4. USE THE AVAILABLE CIRCUITS IN EXISTING CONTROLLERS TO FEED TEMPORARY ROADWAY LIGHTS. CONNECT LIGHTS TO ALTERNATE PHASES. 1.e. L1-N, L2-N.
- 5. CONTRACTOR SHALL REMOVE EXISTING MAST ARMS AND LUMINAIRES DESIGNATED AS R THESE FIXTURES ARE PART OF THE VILLAGE SYSTEM AND SHOULD BE RETURNED TO THE VILLAGE.
- 6. CONTRACTOR SHALL COORDINATE THE LOCATIONS OF WOOD LIGHT POLES WITH THE PROPOSED POLE LOCATIONS SUCH THAT REMOVAL/RELOCATION OF THE TEMPORARY INSTALLATION IS NOT REQUIRED AT THE TIME OF PROPOSED POLE INSTALLATION.
- 7. ALL THE ALUMINUM LIGHT POLES SHOULD BE PROVIDED WITH LUMINAIRE SAFETY CABLE ASSEMBLY.
- 8. CONTRACTOR SHALL USE EXISTING POLES TO SUPPORT TEMPORARY AERIAL CABLE.
- 9. THE CONTRACTOR SHALL BE RESPONSIBLE FOR THE MAINTENANCE OF ALL TEMPORARY LIGHTING WITHIN THE PROJECT LIMITS FOR THE ENTIRE DURATION OF THE PROJECT. ANY DAMAGE INCURRED DURING CONSTRUCTION SHALL BE PROMPTLY REPAIRED SO SERVICE IS NOT DISRUPTED. CONTRACTOR IS RESPONSIBLE FOR VERIFYING THE EXISTING CONDITIONS.
- 10. LOCATIONS OF WOOD LIGHT POLES SHALL BE APPROVED BY THE ENGINEER PRIOR TO INSTALLATION.
- 11. RELOCATION OF THE EXISTING LIGHTING CONTROLLER, IF REQUIRED SHALL BE ACCOMPLISHED IN ONE DAY SO THAT LIGHTING FOR THE INTERSECTION IS NOT INTERRUPTED, ALL AERIAL WIRING AND SERVICE CONNECTIONS SHALL BE IN-PLACE PRIOR TO ACTUAL RELOCATION OF THE CONTROLLER.
- 12. TEMPORARY LIGHTING WHICH WILL NOT REMAIN UPON PROJECT COMPLETION SHALL BE REMOVED ONCE THE PERMANENT LIGHTING IS INSTALLED AND OPERATIONAL REMOVAL OF THE AERIAL CABLE AND TEMPORARY WOOD POLE SHALL BE PAID FOR AS "REMOVAL OF TEMPORARY LIGHTING UNITS". REMOVAL OF THE EXISTING LIGHTING POLES AND LUMINAIRES SHALL BE PAID FOR AS "REMOVAL OF EXISTING LIGHTING UNIT, SALVAGE". SEE PLAN SHEETS FOR SPECIFIC LIGHTING STATUS. CONTRACTOR SHALL ALSO REMOVE ALL NON-PERMANENT LIGHTING FACILITIES REMAINING FROM CONTRACT GOEIO AS PART OF THIS CONTRACT.
- 13. SETBACKS FOR POLES SHALL BE FROM THE BACK OF CURB UNLESS OTHERWISE NOTED ON THE PLANS.
- 14. CONTRACTOR SHALL SPLICE AERIAL CABLE AT LOCATIONS INDICATED TO PERMIT INDICATED CIRCUIT TO BRANCH INTO SIDE STREET.
- 15. CONTRACTOR TO INTERCEPT THE CIRCUIT FROM THE LIGHTING CONTROLLER TO THE EXISTING LIGHTING POLE AND TERMINATE THE SAME ON THE NEW WOOD LIGHT POLE. IF THIS CABLE IS NOT LONG ENOUGH, INSTALL NEW CABLE FROM THE EXISTING CONTROLLER TO THE WOOD LIGHT POLE. REMOVE THE OLD CABLE AND DISPOSE OFF PER CONTRACTUAL REQUIREMENTS.
- 16. NOT USED.
- 17. UNLESS OTHERWISE NOTED, POWER CABLES TO THE EXISTING POLES SHALL BE FED FROM THE EXISTING LIGHTING CONTROLLER, CONTRACTOR TO VERIFY THE CIRCUITRY PRIOR TO MAKING ANY CHANGES.
- 18. NOT USED.
- 19. CONTRACTOR SHALL DISCONNECT THE POLE WIRES ONLY AT THE FUSES, LEAVING THE OTHER CIRCUITRY
  IN TACT TO ENSURE THAT CONTINUITY OF POWER TO THE SUCCEEDING AND PRECEDING POLES IS NOT DISRUPTED.
- 20. UNLESS NEW CABLE CONNECTIONS /MODIFICATIONS ARE SHOWN ON THE TEMPORARY LIGHTING PLANS, CONTRACTOR SHALL VERIFY THE EXISTING CIRCUITRY AND MAINTAIN CONTINUITY OF POWER FOR ALL THE EXISTING POLES.
- 21. IF THE EXISTING LIGHTING POLE IS FED FROM A CONTROLLER LOCATED ON A SIDE STREET, LEAVE THE CIRCUITRY "AS IS" FOR USE AS TEMPORARY LIGHTING FOR U.S. ROUTE 6.
- 22. AERIAL CABLE WHEN USED SHALL BE SECURELY ATTACHED TO EACH LIGHTING POLE. DRILLING INTO THE POLE WILL NOT BE PERMITTED. THE MOUNTING HEIGHT OF THE ATTACHMENT SHALL BE CONSISTENT WITH THE MOUNTING HEIGHT OF THE AERIAL CABLE ON THE TEMPORARY WOOD POLES. THE AERIAL CABLES COMING DOWN THE LIGHTING POLE TO THE EXISTING LIGHTING POLE SHALL BE SECURELY ATTACHED TO THE POLE AS DIRECTED BY THE ENGINEER. THIS WORK WILL NOT BE PAID FOR SEPARATELY BUT SHALL BE INCIDENTAL TO THE COST OF THE AERIAL CABLE.
- 23. REFER TO PLANS FOR LOCATIONS OF TEMPORARY SERVICE WOOD POLES AND TO SHEET 415 FOR DETAILING.

## PAY ITEM LIST

## US ROUTE 6 FROM I-294 TO HALSTED STREET JOB NO. D-91-249-99

JOB NO. D-91-249-99						
CODE NO.	PAY ITEM	UNIT	TOTAL QUANTITY			
82500560	LIGHTING CONTROLLER TYPE CB-RCS	EACH	2			
	200AMP - 480VOLT					
80400100	ELECTRIC SERVICE INSTALLATION	EACH	2			
M8100060	CONDUIT IN TRENCH, 50MM DIA., GALVANIZED STEEL	METER	1315			
M8100070	CONDUIT IN TRENCH, 65MM DIA., GALVANIZED STEEL	METER	224			
M8101060	CONDUIT DUGLED CAMADIA CALVANIZED	METER	69			
IVIO TO TOOU	CONDUIT PUSHED, 65MM DIA., GALVANIZED STEEL	METER	68			
M8160400	UNIT DUCT, WITH 3-1/C NO.4 AND 1/C NO.6 GROUND	METER	1639			
	600V (EPR-TYPE RHW), 30MM DIA. POLYETHYLENE					
M8160415	UNIT DUCT, WITH 3-1/C NO.2 AND 1/C NO.4 GROUND	METER	1123			
	600V (EPR-TYPE RHW), 40MM DIA. POLYETHYLENE					
MX816065	UNIT DUCT, WITH 3-1/C NO.6 AND 1/C NO.6 GROUND	METER	6042			
	600V (EPR-TYPE RHW), 25MM DIA. POLYETHYLENE					
M8170485	ELECTRIC CABLE IN CONDUIT, 600V	METER	3000			
	(EPR-TYPE RHW) 3-1/C NO. 10					
M8170805	ELECTRIC CABLE IN CONDUIT, 600V	METER	77			
	(EPR-TYPE USE) 3-1/C NO. 2					
M8180120	AERIAL CABLE, 3-1/C NO. 2 WITH MESSENGER WIRE	METER	2528			
M8190200	TRENCH AND BACKFILL FOR ELECTRICAL WORK	METER	8655			
82102310	LUMINAIRE, SODIUM VAPOR, HORIZONTAL MOUNT, 310 WATT	EACH	162			
82102400	LUMINAIRE, SODIUM VAPOR, HORIZONTAL MOUNT, 400 WATT	EACH	38			
M8305020	LIGHT POLE, ALUMINUM, 14.5M M.H.,	EACH	134			
	2.5M MAST ARM					
M8307290	LIGHT POLE, WOOD, 15.24 METER, CLASS 4	EACH	2			
M8307300	LIGHT POLE, WOOD, 15.24 METER, CLASS 4,	EACH	38			
	WITH 4.5 METER MAST ARM					
M8360100	LIGHT POLE FOUNDATION, 600MM DIAMETER	METER	536			
M8380095	BREAKAWAY DEVICE, TRANSFORMER BASE	EACH	134			
	381MM BOLT CIRCLE	ļ				
84100110	REMOVAL OF TEMPORARY LIGHTING UNITS	EACH	65			
84200500	REMOVAL OF EXISTING LIGHTING UNIT,	EACH	70			
	SALVAGE					
X0323574	MAINTENANCE OF LIGHTING SYSTEM	CAL MO	18			
X0324387	LUMINAIRE SAFETY CABLE ASSEMBLY	EACH	162			
X8040400	ELECTRIC UTILITY SERVICE CONNECTION	EACH	2			
X8950080	REMOVE EXISTING LIGHTING CONTROLLER	EACH	2			
MX033724	GROUND ROD, 16MM DIA. X 3.0 M	EACH	144			
			, * 1			

Delta Engineering, Inc.

	F.A RTE.	SECTION	COUNTY	TOTAL SHEETS	SHEET NO.
	351	3277R	соок	541	334
			TO STA.		<b></b>
		ILLINOIS FED	. AID PROJ	ECT	

CONTRACT NO. 6

DRAWING No. E-1

CHECKED BY C.K./H.S.

		DRAWING NO. E-		
REVISIONS		ILLINOIS DEPARTMENT OF TRANSPORTATION		
NAME DATE		TEETHOIS BELANTALENT OF THANSFORTATION		
		US RTE 6 FROM I-294 TO IL RTE 1		
		GENERAL NOTES & SUMMARY OF QUANTITY		
		DRAWN BY S.S./W.S.		

DATE 01/28/09