GROUND ELECTRODE MEASUREMENT

GROUNDING TESTS SHALL DONE FOR MANHOLE GROUNDS, GROUND ROD CONNECTIONS AND COUNTERPOISE CONNECTIONS TO ENSURE THE INTEGRITY OF THE ELECTRODE INSTALLATION. TESTING OF THE GROUND SYSTEM AND CONNECTIONS SHALL BE DONE USING THE CLAMP-ON RESISTANCE TEST METHOD FOR GROUND RODS AND COUNTERPOISE.

CLAMP-ON GROUND RESISTANCE TEST (NORMAL TEST)/ THREE POINT FALL OF POTENTIAL TEST (NORMAL TEST)


NAPERVILLE PUBLIC

TESTS SHALL BE PERFORMED WHEN THE GROUND IS NOT FROZEN TO ELIMINATE HIGH RESISTANCE READINGS IN THE MANHIOLES. THE CLAMP ON TEST SHALL BE DONE AT EACH GROUND ROD AND COUNTERPOISE CONNECTION AND FROM THE MANHOLE PERMETER GROUND CABLE TO THE GROUND ROD. ARM CINSTRUMENT MODEL 3710, 3730, OR EQUIPMENT MAY BE USED. THE CLAMP ON GROUNC METER SHALL CLAMPED ON TO THE POWER NEUTRAL BETWEEN THE UTILITY THANSFORMER, POLE GROUND, SWITCH GRAY GROUND AND THE STREET SHALL CLAMPED ON TO THE POWER NEUTRAL BETWEEN THE UTILITY THANSFORMER, POLE GROUND, SWITCH GRAY GROUND AND THE STREE FOROUND. THE USER MUST BE AWARE THAT A O.7 Ω READING INDICATION A CONTINUITY LOOP AND NOT A GROUND RESISTANCE. IF A FOWER NEUTRAL IS NOT CLOSE TO THE NEW INSTALLATION THEN THE THREE POINT FALL OF POTENTIAL, GROUND RESISTANCE CAN BE USED.

ALL TESTING MATERIAL AND TOOLS ARE FURNISHED BY THE CONTRACTOR.
THIS SPECIFICATION IS USED TO TEST HANDHOLES, SWITCH GEAR VALLTS, MANHOLES AND OTHER EQUIPMENT AS DIRECTED.

GROUNDING WITH GROUND RODS (DETAIL)

STANDARD MANHOLE (GROUNDING WITH RODS)




GROUNDING WITH GROUND RODS

C30-1160 TYPE "E" MANHOLE (UGMH) C30-1170 TYPE "G" MANHOLE (UGMH) C30-1140 TYPE "A" MANHOLE (UGMH)


NAPERVILLE PUBLIC UTILITIES DEPARTMENT ELECTRIC STANDARD

CLAMP ON METER TEST STANDARD MANHOLE

(GROUNDING WITH GROUND RODS AND COUNTERPOISE)




PLACEMENT OF METER FOR READING



GROUNDING WITH GROUND RODS

COUNTY TOTAL SHEETS SHEET NO SECTION 1545 00-00115-00-BR DUPAGE 97 83 STA. 1+31.77 O STA, 5+50.00 FED. ROAD DIST. NO. | ILLINOIS | FED. AID PROJECT

SAMPLE INSTALLATION (CLAMP ON METER)



NOTE:

OBSERVE ALL SAFETY REQUIREMENTS AND THEN REMOVE COVERING ON THE GROUND CONDUCTOR IF PRESENT AND PROVIDE SUFFICIENT ROOM FOR THE MODEL 3710/3730 JANS, WHICH MUST BE ABLE TO CLOSE EASILY AROUND THE CONDUCTOR. THE JAWS CAN BE PLACED AROUND THE GROUND ROD ITSELF.
NOTE: THE CLAMP MUST BE PLACED SO THAT THE JAWS ARE IN AN ELECTRICAL PATH FROM THE SYSTEM NEUTRAL OR GROUND WIRE TO THE GROUND ROD, OR COUNTERPOISE.


SELECT THE CURRENT RANGE "A". CLAMP ONTO THE GROUND CONDUCTOR AND MEASURE THE GROUND CURRENT. THE MAXIMUM CURRENT RANGE IS 30 A. IF THE GROUND CURRENT EXCEEDS 5 A., GROUND RESISTANCE MEASUREMENTS ARE NOT POSSIBLE. DO NOT PROCEED FURTHER WITH THE MEASUREMENT, REMOVE THE CLAMP—ON TESTER FROM THE CIRCUIT, NOTING THE LOCATION FOR MAINTENANCE, AND CONTINUE TO THE NEXT TEST LOCATION. RECORD CURRENT ON DATA SHEET.

AFTER NOTING THE GROUND CURRENT, SELECT THE GROUND RESISTANCE RANGE $^\prime\Omega^\prime$ (OHM) and measure the resistance directly. The reading you measure with the 3710/3730 indicates the resistance of the crop, resistance of the counterpoise, but also of the connection to the system neutral and all bonding connections between the neutral and the rod.

RECORD 2 OR 4 RESISTANCE READINGS ON DATA SHEET. IF ANY ONE READING IS ABOVE 25 OHMS, CONTACT DPU-E IMMEDIATELY.
SEND COMPLETED DATA SHEET TO THE PROJECT ENGINEER AND RECORDS.

NAPERVILLE PUBLIC	GROUNDING WITH GROUND RODS	BATE: 05-01-05
UTILITIES DEPARTMENT	Common and	Page 5 of 7
ELECTRIC STANDARDS	(DETAIL)	58199-103

DATA SHEET FOR RECORDING GROUND RESISTANCE BY THE FALL OF POTENTIAL METHOD.



GROUNDING WITH GROUND RODS

DATA SHEET FOR RECORDING GROUND RESISTANCE MEASUREMENT BY THE CLAMP ON GROUND RESISTANCE TEST METHOD

INSTALL INSTALL FEET OF GROUND RODS COUNTERPOISE TOTAL PER LOCATION TOTAL PER LOCATION		GROUND RODS		COUNTERPOISE		MEASURED RESISTANCE OF GROUND RODS AND COUNTERPOISE (OHMS)		i.e. ROCK, CLAY				READING		MEASURED WATER LEVEL IN MANHOLE (FT)	REMARKS		
LOCATION #1	LOCATION #2	LOCATION #1	LOCATION #2	LOCATION #1	LOCATION #2	LOCATION #1	LOCATION #2	LOCATION #1	LOCATION #2	LOCATION #1	LOCATION #2	LOCATION #1	LOCATION #2	LOCATION #1	LOCATION #2		

NOTE:
A HIGH READING INDICATES ONE OR MORE OF THE FOLLOWING:
1) POOR GROUND RODS.
2) OPEN GROUND CONDUCTOR.
3) HIGH RESISTANCE, DUE TO POOR CONNECTIONS ON RODS, HARDWARE & CLAMPS.
4) METER CLAMP IS IMPROPERLY CLOSED.
5) FAULTY METER.

GROUNDING WITH GROUND RODS

DATE:
TYPE OF METER AND MFG.:
MANHOLE NUMBER + TYPE:
POLE NUMBER + SIZE:
STREET ADDRESS:
NAME OF PERSON
PERFORMING TEST:
V.F. #
TEMPEDATURE (AIR)

TEMPERATURE (AR): _____F SIZE OF GROUND RODS: <u>\$78 DIA COPPER CLAD, UNLESS NOTED</u> SIZE OF CABLE FOR GROUND WIRE AND/OR COUNTERPOISE IS <u>4/O COPPER (BARE) 7 STRAND, UNLESS NOTED</u>

CITY OF NAPERVILLE/DEPARTMENT OF PUBLIC UTILITIES - ELECTRIC

PROJECT TITUE BAILEY R	D. BRIDGE		NK INSTALLA	ATION WE INC.	OID PILE JONG 0058199001C17.DWG
COORDIA		TH BRIDG	E IMPROVE	MENT JK	PROJECT NO. EU12-06-04
DATE 05-15 07			199	580 :	COMPLETED IN:
ENGINEER RPS		3°	7 1 3 3 7 1 1 1	SONZ : NTS	SHEET 17 OF 23