

ELECTRICAL NOTES

PART 1: GENERAL

A. DESCRIPTION

Provide all requirements and criteria for safety and reliability to furnish and install complete operating electrical system, including materials, labor, necessary equipment as herein specified. Comply with local codes, National Electrical Code, IDOT, and all applicable codes and standards. The equipment and installation shall confirm with the standard specifications for road and bridge construction of the Illinois Department Of Transportation including latest revision and supplemental specifications, as well as the special

B. Scope of Work

- 1. Contractor shall furnish, install, and test complete street lighting system with all lighting poles, luminaries, foundations, lighting control cabinet, conduits, hangers, supports, devices, wiring, etc., required for a complete and operational installation. After installation, contractor shall completely test all components in compliance with IDOT standards to ensure complete functional installation
- The work shall be performed in accordance with the rules and regulations set forth in the local governing code. The work shall also meet the laws and ordinance required by those agencies having jurisdiction.
- 3. Contractor shall visit the site and make himself thoroughly familiar with existing conditions. Prior to submitting the proposal, include any relocation and/or alternations to the existing electrical system, components or equipment required to accommodate the new
- Contractor shall obtain all permits required to perform his work. Prepare and submit to the authorities any and all data, drawings and details required for approval before commencing the installation.
- Maintain existing street lighting system operation during construction until new construction of street lighting system is completed. Maintain existing lighting as temporary lighting during the construction period. Remove same upon completion of the project.
- 6. Contractor shall coordinate work with all trades and avoid conflicts and delays.
- Notify the engineer in writing of any discrepancies between the existing conditions and the new work. Lack of notification shall indicate that no discrepancies or conflicts
- 8. All light poles shall be non-breakaway type.

DESCRIPTION

METAL HALIDE FIXTURE ON 27 FT. POLE WITH PEDESTRIAN ARM

METAL HALIDE FIXTURE ON 30 FT. POLE WITH PEDESTRIAN ARM

TAG

F1

F2

- 9. Contractor shall coordinate work with utility companies, including electric, water, gas, sewer, cable, etc.
- 10. Rigid Steel Conduit shall be pushed under street or driveway and extended 3'-0" on each side.
- As part of this work Owner shall have first salvage rights to any item removed as part of this project. Dispose of all others. Any unused equipment or wiring will not be allowed to be abandoned in place.
- 12. Red tape or marking shall be 10" below grade to mark electrical conduit routing.
- 13. After construction of new system remove old lighting poles, foundation and wiring. Abandon in place the conduit system.
- 14. The contractor shall be responsible for damage incurred by him in any crea of the project such as pavement, driveways, and sidewalks and shall restore them to their original condition as directed by the engineer. Landscaped areas shall be restored and damaged plant materials replaced to the satisfaction of the engineer.
- Lighting poles shall be located to provide unobstructed access to pedestrians meeting ADA requirements,

MANUFACTURER

STERNBERG-OMEGA

STERNBERG-ÖMEGA

16. Contractor is responsible to identify all underground and overhead utility conflicts and ensure adequate clearances between utilities and new lighting system.

250MHP240/R03H-L/MHP250/ MOG/ED28-MHP70/MED/BK ANTIQUE STREET LAMP EM17RT-70M-MOD-GCF-SR2-240/

MOG/ED28-MHP70/MED/BK
ANTIQUE STREET LAMP EM17RT-70M-MOD-GCF-SR2-240/

CATALOG NUMBER

2-1527RFG/OD/70MHP/RO2H-L/OF/

EM25RT-250M-MOG-GCF-SR3-240/

2-1527RFG/OD/70MHP/RO2H-L/OF/

EM25RT-250M-MOG-GCF-SR3-240/

250MHP240/R03H-L/MHP250/

LIGHTING UNIT SCHEDULE

LAMPS

TYPE

250W METAL HALIDE

70W METAL HALIDE (PEDESTRIAN)

250W METAL HALIDE (STREET LIGHT)

70W METAL HALIDE (PEDESTRIAN)

(STREET LIGHT)

NO.

C. Guarantee

- 1. Guarantee in writing all electrical equipment for a period of one year following date of substantial completion. State the additional amount for a five year full guarantee and full maintenance contract of electrical system.
- All apparatus shall be built and installed so as to deliver its full rated capacity at the efficiency for which it was designed.

D. Construction Phase Submittals

Submit shop drawings to the engineer for approval. Prepare and provide the engineer with a complete set of circuited "record" drawings at project completion. Such drawings shall be submitted on a clear and legible reproducible form.

PART 2: PRODUCTS

A. Quality Level

All material and equipment used for this project shall be UL listed and approved for the intended applications unless otherwise noted.

B. Material

- Unit duct shall be Type MC 600 volt, EPR rated insulation, PVC jacket, Steel interlock armor, copper conductors and color coded.
- 2. Site lighting branch circuits shall be #4 AWG minimum, unless otherwise noted. Control wiring shall be #14 AWG minimum

PART 3: EXECUTION

- Provide a complete properly operating system for each item of equipment called for under this notes. Install in accord with the equipment manufacturer's instructions, the best industry practices and under competent supervision at all time.
- 2. Prior to inspection to determine substantial completion the contractor shall operate cli-electrical system to demonstrate that the installation and performance of the system conform to the requirements specified above and on the drawings.

LEGEND

- Existing street light
- Proposed handhole
- Proposed 27'-0" street light 250W Metal Halide at 240V with 3' pedant arm at 27' high for roadway, & 70W Metal Halide at 240V with 1' pedant arm at 15' high for sidewalk.
- Proposed 30'-0" street light 250W Metal Halide at 240V with 3' pedant arm at 30' high for roadway, & 70W Metal Halide at 240V with 1' pedant arm at 15' high for sidewalk. ••
- Controller, 100A, 240/480V, 1PH, 3W
 - Conduit, pushed, rigid galvanized steel $3'\!-\!0"$ below grade, extend $3'\!-\!0"$ on each side of the curb
 - 3" galvanized steel conduit 3'-0" below grade
- ---- Unit duct (Refer to plan for exact size)
- X_{ER} Existing street light to be removed (light pole and foundation)
- Fixture type
- Proposed vandal proof receptacle (Weatherproof and Ground Fault Interrupter) UL listed, corrosion resistant and cover NEC 406.8.B.2c compliant
- Ground Rod

INPUT

WATTS (240V)

340

340

AMPS

1.42

1.42

Weatherproof, corrusion resistant cabinet. Refer to detail for more information.

MOUNTING

(REFER TO DETAIL

(REFER TO DETAIL

FOR EXACT

FOR EXACT

FIXTURES)

MOUNTING OF


174422	Ontoon nomber	OLE OF BROKEN	THOSE OF ETO TIMEOTIC	(AT 240V)	(AI 240V)
1.4	A	50A, 240V	(5) 340W	1700VA	
A1	В	50A, 240V	(5) 340W		1700VA
(BERWYN) 100A, 240/480V,	С	50A, 240V	(6) 340W	2040VA	///////////////////////////////////////
100A, 240/460V, IPH. 3W	D	50A, 240V	(6) 340W	///////////////////////////////////////	2040VA
1111, 544	E,F,G,H	50A, 240V	SPARE		///////////////////////////////////////
			SUBTOTAL	3740VA	3740VA
		CABINET A1	TOTAL LOAD (480V, 1PH)	7480VA*, 1	
	A	50A, 240V	(6) 340W	2040VA	V////////
A2	В	50A, 240V	(5) 340W	777777777	1700VA
(BERWYN)	C	50A, 240V	(10) 340W	3400VA	11/1/1/1/
100A, 240/480V,		50A, 240V	(11) 340W	111111111111111111111111111111111111111	3740VA
1PH, 3W	E,F,G,H	50A, 240V	SPARE	VIIIIIII	77777777
	L,1, (0,1)	30A, 2-10V	SUBTOTAL	5440VA	5440VA
		CABINET A2	TOTAL LOAD (480V, 1PH)	10880VA, 3	
	Y	T	ye		
B1	В	50A, 240V	SERVE EXISTING LIGHTING	<i>\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\</i>	2700VA
(CICERO)		,	(EAST OF AUSTIN)	<i>\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\</i>	,,,,,,,,,,,
00A, 240/480V,		50A, 240V	(4) 340W	1360VA	
1PH, 3W	D	50A, 240V	(5) 340W	<i>\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\</i>	1700VA
	A,E,F,G,H	50A, 240V	SPARE	Y////////	
			SUBTOTAL	1360VA	4400VA
		CABINET B1	TOTAL LOAD (480V, 1PH)	5760VA, 12	2A
	A	50A, 240V	(5) 340W	1700VA	(//////////////////////////////////////
C1	В	50A, 240V	(6) 340W	V////////	2040VA
(OAK PARK)	C	50A, 240V	(6) 340W	2040VA	
100A, 240/480V, 1PH, 3W	D	50A, 240V	(6) 340W	///////////////////////////////////////	2040VA
11 11, 54	E,F,G,H	50A, 240V	SPARE	<i>\////////////////////////////////////</i>	77777777
			SUBTOTAL	3740VA	4080VA
		CABINET C1	TOTAL LOAD (480V, 1PH)	7820VA*, 1	6.3A
	A	50A, 240V	(7) 340W	2380VA	V////////
C2	В	50A, 240V	(6) 340W	7//////////////////////////////////////	2040VA
(OAK PARK)	C	50A, 240V	(4) 340W	1360VA	77/1/1/1/
100A, 240/480V,	D	50A, 240V	(4) 340W	11/1/1/1/1/	1360VA
1PH, 3W	E,F,G,H	50A, 240V	SPARE	<i>*////////////////////////////////////</i>	77777777
	2,1,10)	007, 2101	SUBTOTAL	3740VA	34COVA
		CADINET CO			
			TOTAL LOAD (480V, 1PH)	7140VA*, 1	4.9A
	A	50A, 240V	(5) 340W	1700VA	
C3	В	50A, 240V	(5) 340W		1700VA
(OAK PARK)	С	50A, 240V	(5) 340W	1700VA	
100A, 240/480V,	D	50A, 240V	(5) 340W	V////////	1700VA
	E,F,G,H	50A, 240V	SPARE		
1PH, 3W	ا اولان اوسا				41111111
1PH, 3W	E,1,0,11		SUBTOTAL	3550VA	3400VA

ELECTRICAL LOAD SCHEDULE

CIRCUIT NUMBER SIZE OF BREAKER NO. OF LTG FIXTURE (AT 240V) (AT 240V)

- C1 Control cabinet number
- B Circuit number
- Pole number of the circuit
- *All poles in bump-outs areas shall be offset from back of curb to centerline of pole as required to be inline with other poles.
- *All poles shall have the same offset from the roadway centerline to maintain visual alignment.
- New foundation and poles shall be located away from any existing utilities. Contractor shall identify all utilities and dig by hand to expose utility lines. Final exact location of foundation and pole shall be coordinated and approved prior to installation.







	7	TERR	A	225	W. OHIO	FOURTH	FL.
	V	ENGINEERING	LTD.			-0123	

POLE & BASE

STRATFORD 22/30/A

RSS/DBA/RSB4/BK WITH STRATFORD BASE

COMPLETE ASSEMBLY N99-B483 (27FT)

STRATFORD 22/32/A/

RSS/DBA/RSB4/BK WITH STRATFORD BASE COMPLETE ASSEMBLY

N99-B483 (30FT)

STATE OF ILLINOIS DEPARTMENT OF TRANSPORTATION

BALLAST VOLT

CWA 240

CWA 240 OD SINGLE ARM FOR PEDESTRIAN

OD SINGLE ARM FOR PEDESTRIAN

OF SINGLE ARM FOR STREET

OF SINGLE ARM FOR STREET

	E	LE	C1	ricai	L NO	ΓES,	LE	GEN	ID	AND	ELEC	CTRICAL	LOAD	SCHED	ULE
COALE		1//		201	CHEET	NO	- 1	OF	20	CUEET	c c	TA		TO CTA	

TLE NAME =	USER NAME = IDOT	DESIGNED - EE	REVISED -
NRT≘38-sht-light@1.dgn		DRAWN - PY	REVISED -
	PLOT SCALE = 20.0000 '/ IN.	CHECKED - JB	REVISED -
	PLOT DATE = 3/11/2010	DATE -	REVISED ~

221 To 249 SECTION COUNTY TOTAL SHEETS 09-00248-00-RS соок 274 CONTRACT NO. 63432 ILLINOIS FED. AID PROJECT SCALE: 1" = 20' SHEET NO. 1 OF 29 SHEETS STA.

VOLTAGE	DROP CAL	CULA	TION	FOF	R CA	BINET A1
PROJECT	ROOSEVELT ROAD		LOCATION		SE OF	HOME AND ROOSEVELT
CABINET	A1		CABLE SIZE		3-1/0	NO.4 & 1-1/C NO.6
CIRCUIT	A		CONDUCTOR	2	COPPE	R
SYSTEM VOLTAGE	480V		LUMINAIRE	VOLTAGE	240V	
NO. OF LUMINAIRES	CURRENT/LUMINAIRE	DISTANC	E 2X	RESIS	TIVITY	VOLTAGE DROP
5	1.42A	267FT	2	0.321	/1000	1.122V
4	1.42A	263FT	2	0.321	/1000	0.959V
3	1.42A	255FT	2	0.321	/1000	0.697V
2	1.42A	233FT	2	0.321	/1000	0.425V
1	1.42A	245FT	2	0.321	/1000	0.223V
				TOTA	AL.	3.522V

TOTAL VOLTAGE DROP/ SYSTEM VOLTAGE +0.734%

VOLTAGE	DROP CAL	CULA	ATION	FOF	R CA	ABINET A1
PROJECT	ROOSEVELT ROAD		LOCATION		SE OF	HOME AND ROOSEVELT
CABINET	A1		CABLE SIZE		3-1/0	NO.4 & 1-1/C NO.6
CIRCUIT	В		CONDUCTOR	2	COPPE	
SYSTEM VOLTAGE	480V		LUMINAIRE	VOLTAGE	240V	
NO. OF LUMINAIRES	CURRENT/LUMINAIRE	DISTANC	E 2X	RESIS	TIVITY	VOLTAGE DROP
5	1.42A	129FT	2	0.321	/1000	0.589V
4	1.42A	288FT	2	0.321	/1000	1.050V
3	1.42A	242FT	2	0.321	/1000	0.662V
2	1.42A	237FT	2	0.321	/1000	0.432V
1	1.42Ą	241FT	2	0.321	/1000	0.219V
				TOTA	71	2.952V

TOTAL VOLTAGE DROP/ SYSTEM VOLTAGE =0.615%

VOLTAGE	DROP CAL	CULA	TION	FOF	C C	ABINET A1
PROJECT	ROOSEVELT ROAD		LOCATION		SE OF	HOME AND ROOSEVELT
CABINET	A1 ·		CABLE SIZE		3-1/0	NO.4 & 1-1/C NO.6
CIRCUIT	C		CONDUCTOR	?	COPPE	R
SYSTEM VOLTAGE	480V		LUM:NAIRE	VOLTAGE	240V	
NO. OF LUMINAIRES	CURRENT/LUMINAIRE	DISTANC	E 2X	RESIS	TIVITY	VOLTAGE DROP
6	1.42A	26FT	2	0.321	/1000	0.142V
5	1.42A	226FT	2	0.321	/1000	1.030V
4	1.42A	243FT	2	0.321	/1000	0.886V
3	1.42A	239FT	2	0.321	/1000	0.654V
2	1.42A	248FT	2	0.321	/1000	0.452V
1	1.42A	276FT	. 2	0.321	/1000	0.252V
				TOTA	VL.	3,416V

TOTAL VOLTAGE DROP/ SYSTEM VOLTAGE =0.712%

VOLTAGE	DROP CAL	CULA	NOITA	FOF	R CA	ABINET A1
PROJECT	ROOSEVELT ROAD		LOCATION		SE OF	HOME AND ROOSEVELT
CABINET	A1 5		CABLE SIZE	=	3-1/C	NO.4 & 1-1/C NO.6
CIRCUIT	D		CONDUCTO	R	COPPE	R
SYSTEM VOLTAGE	480V		LUMINAIRE	VOLTAGE	240V	
NO. OF LUMINAIRES	CURRENT/LUMINAIRE	DISTANO	DE 2X	RESIS	STIVITY	VOLTAGE DROP
6	1.42A	139FT	2	0.321	/1000	0.760V
5	1.42A	243FT	2	0.321	/1000	1.108V
4	1.42A	227FT	2	0.321	/1000	0.828V
3	1.42A	239FT	2	0.321	/1000	0.654V
2	1.42A	248FT	2	0.321	/1000	0.452V
1	1.42A	. 276FT	2	0.321	/1000	0.252V
				TOT	AL	4.053V

TOTAL VOLTAGE DROP/ SYSTEM VOLTAGE =0.844%

VOLTAGE	DROP CALC	CULA	ATION	FOR	CA	BINET A2
PROJECT	ROOSEVELT ROAD		LOCATION		SE OF	EAST AND ROOSEVE
CABINET	A2		CABLE SIZE		3-1/C	NO.4 & 1-1/C NO
CIRCUIT	A		CONDUCTOR	?	COPPER	₹ .
SYSTEM VOLTAGE	480V		LUMINAIRE	VOLTAGE	240V	
NO. OF LUMINAIRES	CURRENT/LUMINAIRE	DISTANO	DE 2X	RESIS	YTIVIT	VOLTAGE DROP
6	1.42A	66FT	2	0.321	/1000	0.361V
5	1.42A	261FT	2	0.321	/1000	1.190V
4	1.42A	270FT	2	.0.321	/1000	0.985V
3	1.42A	249FT	2	0.321	/1000	0.681V
2	1.42A	279FT	2	0.321	/1000	0.509V
1	1.42A	208FT	2	0.321	/1000	0.190V
				TOTA	ĄL	3.915V

TOTAL VOLTAGE DROP/ SYSTEM VOLTAGE =0.816%

VOLTAGE	DROP CALO	CULA	NOIT	FOR	CA	BINET A2
PROJECT	ROJECT ROOSEVELT ROAD				SE OF	EAST AND ROOSEVELT
CABINET	A2	CABLE SIZE		3-1/C NO.4 & 1-1/C NO.6		
CIRCUIT	В .		CONDUCTOR	2	COPPER	
SYSTEM VOLTAGE	480V		LUMINAIRE	VOLTAGE	240V	
NO. OF LUMINAIRES	CURRENT/LUMINAIRE	DISTANC	E 2X	RESIS	TIVITY	VOLTAGE DROP
5	1.42A	197FT	2	0.321	/1000	0.898V
4	1.42A	260FT	2	0.321	/1000	0.948V
3	1.42A	278FT	2	0.321	/1000	0.760V
2	1.42A	260FT	2	. 0.321		0.474V
1	1.42A	258FT	2	0.321	/1000	0.235V
				TOTA	AL.	3.316V

TOTAL VOLTAGE DROP/ SYSTEM VOLTAGE =0.691%

VOLTAGE	DROP CAL	CULA	۱T۵	ON	FOR	CA	BINET A2	
PROJECT	ROOSEVELT ROAD		LOCATION			SE OF EAST AND ROOSEVELT		
CABINET	A2	2				3-1/C	NO.2 & 1-1/C NO.4	
CIRCUIT	С		CON	DUCTOR	2	COPPE	₹ .	
SYSTEM VOLTAGE	480V	LUM	INAIRE	VOLTAGE	240V			
NO. OF LUMINAIRES	CURRENT/LUMINAIRE	DISTAN	CE.	2X	RESIS	TIVITY	VOLTAGE DROP	
10	1.42A	232F1	-	2	0.201	/1000	1.324V	
9	1.42A	243F1		2	0.201	/1000	1.248V	
8	1.42A	273F1	-	2	0.201	/1000	1.247V	
7	1.42A	272F7	*	2	0.201	/1000	1.087V	
6	1.42A	245FT	-	2	0.201	/1000	0.8397,- "	
5	1.42A	154F7		2	-0.201	/1000	0.440V	
4	1.42A	265F1	-	2	0.201	/1000	0.6057	
3	1.42A	266F7	-	2	0.201	/1000	0.456V	
2	1.42A	272F	-	2	0.201	/1000	0.311V	
1	1.42A	258F1	-	2	0.201	/1000	0.147V	
					TOTA	ΔL	7.703V	

TOTAL VOLTAGE DROP/ SYSTEM VOLTAGE = 1.605%

VOLTAGE	DROP CALC	CUL	ΔTI	ON	FOR	CA	BINET A2	
PROJECT	ROOSEVELT ROAD		LOCATION			SE OF EAST AND ROOSEVELT		
CABINET	A2	2				3-1/0	NO.2 & 1-1/C`NO.4	
CIRCUIT	D		CON	IDUCTOR		COPPE	R	
SYSTEM VOLTAGE	480V		LUMINAIRE VOLTAGE			240V		
NO. OF LUMINAIRES	CURRENT/LUMINAIRE	DISTAN	CE	2X	RESIS	TIVITY	VOLTAGE DROP	
. 11	1.42A	74FT		2	0.201	/1000	0.464V	
10	1.42A	259F	Γ	2	0.201	/1000	1.478V	
9	1.42A	268F	Г	2	0.201	/1000	1.377V	
8	1.42A	280F	Γ	2	0.201/1000		1.279V	
7	1.42A	240F	Γ	2	0.201	/1000	0.959V	
.6	1.42A	220F	Г	2	0.201	/1000	0.754V	
5	1.42A	200F	Γ	2	0.201	/1000	0.571V	
4	1.42A	269F	ſ	2	0.201	/1000	0.614V	
3	1.42A	264F	Γ	2	0.201	/1000	0.452V	
2	1.42A	272F	Г	2		/1000	0.311V · ·	
1	1,42A	265F	Γ	2	0.201	/1000	0.151V	
					TOT	4L	8.410V	

TOTAL VOLTAGE DROP/ SYSTEM VOLTAGE =1.752%

VOLTAGE	DROP CAL	CUL	ΔΤΙ	ON	FOF	R CA	ABINET B.1.
ROJECT	ROOSEVELT ROAD		LOC.	ATION		SW OF .	AUSTIN AND ROOSEVELT
CABINET	B1		CAB	LE SIZE		.3-1/C	NO.4 & 1-1/C NO.6
CIRCUIT	C		CONDUCTOR COPPE			R	
SYSTEM VOLTAGE	STEM VOLTAGE 480V			LUMINAIRE VOLTAGE 240V			
NO. OF LUMINAIRES	CURRENT/LUMINAIRE	DISTAN	CE	2X	RESIS	STIVITY	VOLTAGE DROP
4	1.42A	368FT		2	0.321	/1000	1.342V
3	1.42A	279FT	- 1	2	0.321	/1000	0.763V
2	1.42A	254FT		2	0.321	/1000	0.463V
1	1.42A	244FT		2	0.321	/1000	0.222V
					TOT	AL	2.791V

TOTAL VOLTAGE DROP/ SYSTEM VOLTAGE =0.581%

VOLTAGE	DROP CAL	CULA	NOITA	FOF	R CA	ABINET B1	
PROJECT ROOSEVELT ROAD			LOCATION		SW OF AUSTIN AND ROOSEVELT		
CABINET	B1				3-1/C NO.4 & 1-1/C NO.6		
CIRCUIT D CONDUC			CONDUCTOR	R COPPER			
SYSTEM VOLTAGE 480V			LUMINAIRE VOLTAGE 240V				
NO. OF LUMINAIRES	CURRENT/LUMINAIRE	DISTANC	E 2X	RESIS	TIVITY	VOLTAGE DROP	
5	1.42A	233FT	2	0.321	/1000	1.062V	
4	1.42A	277FT	2	0.321	/1000	1.010V	
3	1.42A	248FT	2	0.321/1000		0.678V	
2	1.42A	274FT	2	0.321	/1000	0.500V	
1	1 1.42A 26		2	0.321	/1000	0.240V	
				TOT	AL	2.490V	

TOTAL VOLTAGE DROP/ SYSTEM VOLTAGE =0.727%

EXISTING TRAFFIC CABINET AT AUSTIN & ROOSEVELT

VOLIAGE	DITOI CAL	JULAI	IOIA	run U	ADINE! DA
PROJECT	ROOSEVELT ROAD	LO	CATION	SE OF	AUSTIN AND ROOSEVELT
CABINET	BA	CA	BLE SIZE	2-1/	C NO.6 &1-1/C NO.6 G
CIRCUIT	A	co	NDUCTOR	COPI	PER
SYSTEM VOLTAGE	120V	LUI	MINAIRE	VOLTAGE 120\	/
NO. OF LUMINAIRES	CURRENT/LUMINAIRE	DISTANCE	2X	RESISTIVITY	VOLTAGE DROP
1	3.33A	130FT	2	0.510/1000	0.44V
				TOTAL	0.44V

TOTAL VOLTAGE DROP/ SYSTEM VOLTAGE =0.36%

Highway Lighting Voltage Drop Calculations

 $V_{d} = 2(D) (I) (R)$

V_d = Voltage Drop

= Length of cable

2 = Multiplier; since current leaves and returns

I = Total current in segment

R = DC Resistance of the coble

 $\%V_{d} = \frac{V_{d}}{480} (100)$

	TERRA
1	ENGINEERING LTD.

225 W. OHIO ST., FOURTH FL. CHICAGO, IL 60654 (312)467-0123

STATE OF ILLINOIS
DEPARTMENT OF TRANSPORTATION

4.7					
	F.A.P. RTE.	SECTION	COUNTY	TOTAL S	SHEET NO.
VOLTAGE DROP CALCULATION FOR CABINETS	347	09-00248-00-RS	соок	274	222
SCALE: 1" = 20' SHEET NO. 2 OF 29 SHEETS STA. TO STA.			CONTRACT	T NO. 63	3432
SCALE: 1" = 20' SHEET NO. 2 OF 29 SHEETS STA. TO STA.		ILLINOIS FED. AI	D PROJECT		

FILE NAME :: DIRTE38-sht-light02.dgn
 USER NAME = 100T
 DESIGNED - EE
 REVISED

 DRAWN - PY
 REVISED

 PLOT SCALE = 8.2000 '/ IN.
 CHECKED - JB
 REVISED

 PLOT DATE = 3/11/2010
 DATE - REVISED REVISED

VOLTAGE	DROP CAL	CULA	ATION	FOF	R CA	ABINET C1	
PROJECT	ROOSEVELT ROAD		LOCATION		NE OF HOME AND ROOSEVELT		
CABINET	C1	CABLE SIZE	-	3-1/C NO.4 & 1-1/C NO.6			
CIRCUIT	A		CONDUCTOR	5	COPPE	R	
SYSTEM VOLTAGE	480V		LUMINAIRE	VOLTAGE	240V		
NO. OF LUMINAIRES	CURRENT/LUMINAIRE	DISTANC	E 2X	RESIS	TIVITY	VOLTAGE DROP	
5	1.42A	192FT	2	0.321	/1000	0.875V	
4	1.42A	265FT	2	0.321	/1000	0.966V	
3	1.42A	260FT	2	0.321	/1000	0.711V	
2	1.42A	231FT	2	0.321	/1000	0.421V	
1	1.42A	238FT	2	0.321	/1000	0.217V	
				TOT	AL	3.191V	

TOTAL VOLTAGE DROP/ SYSTEM VOLTAGE =0.665%

VOLTAGE	DROP CAL	CUL	4Τ	ON	FOR	R CA	ABINET C1		
PROJECT	ROOSEVELT ROAD			LOCATION			NE OF HOME AND ROOSEVELT		
CABINET	C1 .		CAB	LE SIZE		3-1/0	NO.4 & 1-1/C NO.6		
CIRCUIT	В			CONDUCTOR			R		
SYSTEM VOLTAGE	480V		LUM	IINAIRE	VOLTAGE	240V			
NO. OF LUMINAIRES	CURRENT/LUMINAIRE	DISTAN	CE	2X	RESIS	TIVITY	VOLTAGE DROP		
6	1.42A	58FT		2	0.321	/1000	0.317V		
5	1.42A	261F1	ſ	2	0.321	/1000	1,190V		
4	1.42A	266FT	Γ	2 -	0.321	/1000	0.970V		
3	1.42A	248F	Γ	2	0.321	/1000	0.678V		
2	1.42A	233F1	ſ	2	0.321	/1000	0.425V .		
1 .	1.42A	255F1	Γ	2	0.321	/1000	0.232V		
					TOTA	AL.	3.812V		

TCTAL VOLTAGE DROP/ SYSTEM VOLTAGE =0.794%

VOLTAGE	DROP CAL	CUL	4TI	ON	FOR	C C	ABINET C1
PROJECT	ROOSEVELT ROAD		LOC	ATION		NE OF	HOME AND ROOSEVELT
CABINET	C1		CAB	LE SIZE		3-1/C	NO.4 & 1-1/C NO.6
CIRCUIT	C		CON	DUCTOR	5	COPPE	R
SYSTEM VOLTAGE	480V		LUM	IINAIRE	VOLTAGE	240V	
NO. OF LUMINAIRES	CURRENT/LUMINAIRE	DISTAN	CE	2X	RESIS	TIVITY	VOLTAGE DROP
6	1.42A	62FT		2	0.321	/1000	0.339V
5	1.42A	235F	-	2	0.321	/1000	1.071V
4	1.42A	240F	-	2	0.321	/1000	0.875V
3	1.42A	238F	-	2	0.321	/1000	0.651V
2	1.42A	241F	-	2	0.321	/1000	0.439V
1	1.42A	288F	-	2	0.321	/1000	0.263V
					TOTA	AL.	3.638V .

TOTAL VOLTAGE DROP/ SYSTEM VOLTAGE =0.758%

VOLTAGE	DROP CAL	CULA	NOITA	FOF	S CA	ABINET C1
PROJECT	ROOSEVELT ROAD		LOCATION		NE OF	HOME AND ROOSEVELT
CABINET	C1		CABLE SIZ	Ε	3-1/0	NO.4 & 1-1/C NO.6
CIRCUIT	D		CONDUCTO	R	COPPE	R
SYSTEM VOLTAGE	480V		LUMINAIRE	VOLTAGE	240V	
NO. OF LUMINAIRES	CURRENT/LUMINAIRE	DISTANO	DE 2X	RESIS	STIVITY	VOLTAGE DROP
6	1.42A	182FT	2	0.321	/1000	1.000V
5	1.42A	235FT	2	0.321	/1000	1.071V
4	1.42A	238FT	2	0.321	/1000	0.868V
3	1.42A	240FT	2	0.321	/1000	0.656V
2	1.42A	247FT	2	0.321	/1000	0.450V
11	1.42A	67FT	2	0.321	/1000	0.061V
				TOT	A,L	4.102V

TOTAL VOLTAGE DROP/ SYSTEM VOLTAGE =0.855%

VOLTAGE	DROP CALC	CULA	NOITA	FOR	CA	BINET C2	
PROJECT	ROOSEVELT ROAD		LOCATION		NW OF SCOVILLE AND ROOSEVELT		
CABINET	C2	CABLE SIZE		3-1/0	NO.4 & 1-1/C NO.6		
CIRCUIT	A		CONDUCTOR	₹	COPPER		
SYSTEM VOLTAGE	480V		LUMINAIRE	VOLTAGE	240V		
NO. OF LUMINAIRES	CURRENT/LUMINAIRE	DISTAN	CE 2X	RESIS	TIVITY	VOLTAGE DROP	
7	1.42A	20FT	2	0.321	/1000	0.128V	
6	1.42A	264F1	Г 2	0.321	/1000	1.444V	
5	1.42A	276F1	Г 2	0.321	/1000	1.258V	
4	1.42A	260FT	Г 2	0.321	/1000	0.948V	
3	1.42A	268F7	г 2	0.321	/1000	0.733V	
2	1.42A	268FT	Г 2		/1000	0.489V	
1	1.42A	258F1	2	0.321	/1000	0.235V	
	1			TOT.	ΔL	5.235V .	
				OTAL MO	TAGE D	DOD / OVOTELL LIGHTAGE	

TOTAL VOLTAGE DROP/ SYSTEM VOLTAGE =1.091%

VOLTAGE	DROP CAL	CULA	NOITA	FOR	CA	BINET	C2		
PROJECT	ROOSEVELT ROAD						NW OF SCOVILLE AND ROOSEVELT		
CABINET	C2	CABLE SIZE		3-1/0	NO.4 & 1-1	/C NO.6			
CIRCUIT	В		CONDUCTOR	?	COPPER				
SYSTEM VOLTAGE	480V		LUMINAIRE VOLTAGE 240V						
NO. OF LUMINAIRES	CURRENT/LUMINAIRE	DISTANO	DE 2X	RESIS	YTIVITE	VOLTAGE	DROP		
6	1.42A	148FT	2	0.321	/1000	0.8	10V		
5	1.42A	282FT	2	0.321	/1000	1.28	35V		
4	1.42A	258FT	2	0.321	/1000	0.9	41V		
3	1.42A	271FT	2	0.321	/1000	0.74	41V		
2	1.42A	272FT	2		/1000	0.49			
1	1.42A	253FT	2	0.321	/1000	0.2.	31V		
				TOT	AL	4.50)4V		

TOTAL VOLTAGE DROP/ SYSTEM VOLTAGE =0.938%

VOLTAGE	DROP CALC	CULA	ITA	ON	FOR	CA	BINET	C2 .
PROJECT	ROOSEVELT ROAD		LOC	ATION		NW OF !	SCOVILLE AND	ROOSEVELT
CABINET	C2		CAB	LE SIZE		3-1/C	NO.4 & 1-1/	C NO.6
CIRCUIT	T C CO			NDUCTOR COPPER				
SYSTEM VOLTAGE	480V		LUMINAIRE VOLTAGE			240V		
NO. OF LUMINAIRES	CURRENT/LUMINAIRE	DISTAN	CE	2X	RESIS	STIVITY	VOLTAGE	DROP
4	1.42A	125F		2	0.321	/1000	0.45	6V
3	1.42A	269F	-	2	0.321	/1000	0.73	5V
2	1.42A	276F	•	2	0.321	/1000	0.50	3V
1	1.42A	241F	-	2	0.321	/1000	0.22	VC
					TOT	Al	1.914	1V

TOTAL VOLTAGE DROP/ SYSTEM VOLTAGE = C.399%

VOLTAGE	DROP CALC	CULA	TION	FOR	CA	BINET C2
PROJECT	ROOSEVELT ROAD		LOCATION		NW OF S	SCOVILLE AND ROOSEVELT
CABINET	C2		CABLE SIZE		3-1/C	NO.4 & 1-1/C NO.6
CIRCUIT	D		CONDUCTOR		COPPE	₹
SYSTEM VOLTAGE	480V	-	LUMINAIRE \	OLTAGE	240V	,
NO. OF LUMINAIRES	CURRENT/LUMINAIRE	DISTANC	E 2X	RESIS	TIVITY	VOLTAGE DROP
4	1.42A	255FT	2	0.321	/1000	0.923V
3	1.42A	277FT	2	0.321	/1000	0.758V
2	1.42A	259FT	2	0.321	/1000	0.472V
1	1.42A	287F	2	0.321	/1000	0.262V
				TOT.	4L.	2.421V

TOTAL VOLTAGE DROP/ SYSTEM VOLTAGE =0.504%

VOLTAGE	DROP	CALC	CULA	\TI	ON	FOR	CA	BINET C3
PROJECT	ROOSEVELT ROAD				LOCATION			LOMBARD AND ROOSEVELT
CABINET C3				CAB	LE SIZE		3-1/0	NO.4 & 1-1/C NO.6
CIRCUIT A				CON	DUCTOR		COPPE	₹
SYSTEM VOLTAGE	480V			LUM	IINAIRE 1	VOLTAGE	240V	
NO. OF LUMINAIRES	CURRENT/	LUMINAIRE	DISTAN	CE	2X	RESIS	TIVITY	VOLTAGE DROP
5	1.42	2A	77FT		2	0.321	/1000	0.351V
4	1.4:	2A	265FT	-	2	0.321	/1000	0.966V
3	1.43	2A	266FT	-	2	0.321	/1000	0.727V
2	1.4:	2A	269FT	-	2	0.321	/1000	0.490V
1	1.4:	2A	260F1	-	2	2 0.321		0.237V
						TOT	4L	2.772V

TOTAL VOLTAGE DROP/ SYSTEM VOLTAGE =0.578%

VOLTAGE	DRO	P CALC	CULA	ITA	ON	FOR	CA	BINET C3	
PROJECT ROOSEVELT ROAD				LOCATION			NW OF	LOMBARD AND ROOSEVELT	
CABINET	C3						3-1/0	NO.4 & 1-1/C NO.6	
CIRCUIT	В		CON	IDUCTOR	3	COPPER			
SYSTEM VOLTAGE	480V			LUN	INAIRE	VOLTAGE	240V		
NO. OF LUMINAIRES	CURRE	NT/LUMINAIRE	DISTAN	CE	2X	RESIS	TIVITY	VOLTAGE DROP	
5		1.42A	217FT	-	2	0.321	/1000	0.989V	
4		1.42A	240F1		2	0.321	/1000	0.875V	
3		1.42A	300FT	-	2	0.321	/1000	0.820V	
2		1.42A	250F1	-	2	0.321	/1000	0.456V	
1		1.42A	258F1		2	0.321	/1000	0.235V	
						TOTA	\L	3.376V	

TOTAL VOLTAGE DROP/ SYSTEM VOLTAGE =0.703%

VOLTAGE	DROP CALC	CULA	ITA	ΟN	FOR	CA	BINET C3			
PROJECT ROOSEVELT ROAD			LOCATION			NW OF LOMBARD AND ROOSEVELT				
CABINET	C3		CABI	LE SIZE		3-1/C NO.4 & 1-1/C NO.6				
CIRCUIT	С			DUCTOR		COPPE	R			
SYSTEM VOLTAGE 480V			LUM	INAIRE '	VOLTAGE	240V				
NO. OF LUMINAIRES	CURRENT/LUMINAIRE	DISTANO	Œ	2X	RESIS	TIVITY	VOLTAGE DROP			
5	1.42A	198FT		2	0.321	/1000	0.903V			
4	1.42A	254FT		2	0.321	/1000	0.926V			
3	1.42A	288FT		2	0.321	/1000	0.788V			
2	1.42A	260FT		2	0.321,	/1000	0.474V			
1	1.42A	250FT		2	0.321/1000		0.227V			
					TOTA	VL.	3.318V			

TOTAL VOLTAGE DROP/ SYSTEM VOLTAGE =0.691%

VOLTAGE	DROP CALC	CULA	NOITA	FOR	CA	BINET C3
PROJECT	ROOSEVELT ROAD		LOCATION		NW OF	LOMBARD AND ROOSEVELT
CABINET	C3		CABLE: SIZ	E	3-1/C	NO.4 & 1-1/C NO.6
CIRCUIT	D		CONDUCTO	R	COPPE	R
SYSTEM VOLTAGE	480V		LUMINAIRE	VOLTAGE	240V	
NO. OF LUMINAIRES	CURRENT/LUMINAIRE	DISTAN	CE 2X	RESIS	TIVITY	VOLTAGE DROP
5	1.42A	71FT	2	0.321	/1000	0.324V
4	1.42A	260FT	2	0.321	/1000	0.948V
3	1.42A	246FT	- 2	0.321	/1000	0.673V
2	1.42A	293FT	2	0.321	/1000	0.534V
1	1.42A	250FT	2	0.321	/1000	0.228V
				TOT	4L	2.707V

TOTAL VOLTAGE DROP/ SYSTEM VOLTAGE =0.564%

Highway Lighting Voltage Drop Calculations

 $V_{d} = 2(D) (I) (R)$

V_d = Voltage Drop

D = Length of cable

2 = Multiplier; since current leaves and returns


I = Total current in segment
R = DC Resistance of the cable

 $%V_{d} = \frac{V_{d}}{480} (100)$

	1			TERRA 225 W. OHIO ST., FOURTH FL. CHICAGO, IL 60654 (312)467-0123
FILE NAME =	USER NAME = IDOT .	DESIGNED - EE	REVISED -	
01RTE38-sht-light@3.dgn		DRAWN - PY	REVISED -	STATE OF ILLINOIS
	PLOT SCALE = 20.0000 '/ EN.	CHECKED - JB	REVISED -	DEPARTMENT OF TRANSPORTATION
· ·				

OF ILLINOIS OF TRANSPORTATION				. 1	OLTAGE DRO	RO	P	CAL	.CULATI	ON	
	SCALE:	1"	=	20′	SHEET	NO.	3	OF	29	SHEETS	ST

VOLTAGE DROP CALCULATION FOR CABINETS	F.A.P. RTE.	SECTION	COUNTY	TOTAL SHEETS	SHEET NO.
VULIAGE DRUP CALCULATION FOR CADINETS	347	09-00248-00-RS	COOK	274	223
W DOV CUETT NO 7 OF DO CUETTO CTA	-		CONTRACT	NO.	63432
1" = 20' SHEET NO. 3 OF 29 SHEETS STA. TO STA.		ILLINOIS FED. AI	D PROJECT		



ITEM	QUANTITY	MAIN CIRCUIT, 1 POLE, 240 VOLT
A	1	MAIN CIRCUIT, 1 POLE, 240 VOLT 5AMP,FRAME. 5AMP NON-INTERCHANGEABLE TRIP INTERRUPTING RATING NEMA-22000 AMP. AT 240 VOLT.
В	1	1.5 KVA, SINGLE PHASE, ENCAPSULATED TRANSFORMER 240X480/120X240 VOLT, 60 HZ. TRIP INTERRUPTING RATING NEWA—22000 AMP. AT 240 VOLT.
С	2	COPPER GROUND BUS 1/4" X1" X 6" LONG MOUNTED ON PANEL WITH LLGS AND SPARE LUGS
D	1	BRANCH CIRCUIT, 1 POLE, 120 VOLT 20AMP,FRAME. 20AMP NON-INTERCHANGEABLE TRIP INTERRUPTING RATING NEMA-22000 AMP. AT 120 VOLT.

WIRING DIAGRAM FOR J1 CABINET

SEE NOTE 11

FOR ONE RECEPTACLE

N.T.S. REFER TO LANDSCAPE PLAN FOR EXACT LOCATION OF CABINET, HANDHOLE, AND RECEPTACLE. FINAL LOCATION TO BE COORDINATED WITH LANDSCAPE ARCHITECT.

- 2-1/C NO.10 &


1-1/C NO. 10 GRD IN 3/4" DIA UNIT DUCT

LEGEND

- Proposed handhole
- Proposed vandal proof receptacle (Weatherproof and Ground Fault Interrupter) UL listed, corrosion resistant and cover NEC 406.8.B.2a compliant

- 1. ALL EXTERNAL HARDWARE SHALL BE STAINLESS STEEL.
- 2. THE HEADS OF CONNECTORS SCREWS SHALL BE PAINTED WHITE FOR NEUTRAL BAR CONNECTION AND GREEN FOR CROUND BAR CONNECTORS.
- 3. ALL WIRING WITHIN THE CABINET SHALL BE COLOR CODED AS INDICATED
- R = RED BL = BLUE W = WHITE FOR NEUTRALB = BLACK Y = YELLOW G = GREEN FOR GROUND
- 4. PROVIDE SEALING GROMMETS FOR ALL OPEN WIRING EXTENDED FROM DEVICES IN BOXES OR CABINETS WITHIN THE CONTROL CABINET.
- 5. ALL WIRING SHALL BE NEATLY DRESSED AND SUPPORTED.
- 6. FOUNDATION SIZE SHALL BE COORDINATED WITH CABINET SIZE AND MFR.
- 7. DOOR SHALL BE CONSTRUCTED FROM SAME TYPE OF MATERIAL AND THICKNESS AS CABINET. 8. DOOR SHALL BE EQUIPPED WITH THREE POINT
- LATCHING MECHANISM WITH NYLON ROLLERS AT TOP THE BOTTOM. 9. DOOR HINGE SHALL BE A HEAVY GAUGE
- CONTINUOUS HINGE WITH A 1/4" (6.35 mm)
 DIA. STAINLESS STEEL HINGE PIN.
- 10. CABINETS SHALL BE PRIMED AND PAINTED
- 11. ALL CONNECTIONS SHALL BE ABOVE GROUND (NO UNDERGROUND SPLICING)
- 12. REFER TO LANDSCAPE PLANS FOR EXACT LOCATION OF RECEPTACLE ENCLOSURE.

 RECEPTACLES ENCLOSURE SHALL NOT BE INSTALLED ON THE SIDEWALK OR AT GRADE LEVELS CAUSING SAFETY HAZARDS OR OBSTRUCTIONS TO PEDESTRIANS.






TERRA
225 W. OHIO ST., FOURTH FL.
CHICAGO, IL 60654
(312)467-0123

DESIGNED - EE REVISED FILE NAME = USER NAME = IDOT 1RTE38-sht-light04.dgn DRAWN - PY REVISED PLOT SCALE = 20.0000 '/ IN. CHECKED - JB REVISED PLOT DATE = 3/11/2010 DATE REVISED

STATE OF ILLINOIS **DEPARTMENT OF TRANSPORTATION**

MIDING	DIACE	3 A R.S.	END	DEC	EDT	ACLE	CADINET	EOD	ONE	RECEPTACLE	F.A. RTE
WINING	DIAGI	JAIVI	run	NEU	EFI	MULE	CADINE	run	OIAE	NEGEPTAGLE	34
SCALE: 1" =	20'	SHEET	NO	1 OF	29	SHEETS	STA.		TO	STA.	1-

SECTION COUNTY TOTAL SHEE SHEETS NO. 09-00248-00-RS COOK 274 224 CONTRACT NO. 63432 ILLINOIS FED. AID PROJECT



WIRING DIAGRAM FÖR J1 CABINET

FOR TWO RECEPTACLE

N.T.S. REFER TO LANDSCAPE PLAN FOR EXACT LOCATION OF CABINET, HANDHOLE, AND RECEPTACLE. FINAL LOCATION TO BE COORDINATED WITH LANDSCAPE ARCHITECT.

ITEM	QUANTITY	MAIN CIRCUIT, 1 POLE, 240 VOLT
A	1	MAIN CIRCUIT, 1 POLE, 240 VOLT 5AMP, FRAME. 5AMP NON—INTERCHANGEABLE TRIP INTERRUPTING RATING NEMA—22000 AMP. AT 240 VOLT.
3	1	1.5 KVA, SINGLE PHASE, ENCAPSULATED TRANSFORMER 240X480/120X240 VOLT, 60 HZ. TRIP INTERRUPTING RATING NEMA-22000 AMP. AT 240 VOLT.
С	2	COPPER GROUND BUS 1/4" X1" X 6" LONG MOUNTED ON PANEL WITH LUGS AND SPARE LUGS
Э	1	BRANCH CIRCUIT, 1 POLE, 120 VOLT 20AMP, FRAME. 20AMP NON-INTERCHANGEABLE TRIP INTERRUPTING RATING NEMA-22000 AMP. AT 120 VOLT.

LEGEND

Proposed handhole

Proposed vandal proof receptacle (Weatherproof and Ground Fault Interrupter) UL listed, corrosion resistant and cover NEC 406.8.B.2a compliant

Ground Rod

ENGINEERING LTD.

TERRA 225 W. OHIO ST., FOURTH FL. CHICAGO, IL 60654 (312)467-0123


STATE OF ILLINOIS DEPARTMENT OF TRANSPORTATION

- 1. ALL EXTERNAL HARDWARE SHALL BE STAINLESS STEEL.
- 2. THE HEADS OF CONNECTORS SCREWS SHALL BE PAINTED WHITE FOR NEUTRAL BAR CONNECTION AND GREEN FOR GROUND BAR CONNECTORS.
- 3. ALL WIRING WITHIN THE CABINET SHALL BE COLOR CODED AS INDICATED
- R = RED BL = BLUE W = WHITE FOR NEUTRAL $B \approx BLACK$ Y = YELLOW G = GREEN FOR GROUND
- 4. PROVIDE SEALING GROMMETS FOR ALL OPEN WIRING EXTENDED FROM DEVICES IN BOXES OR CABINETS WITHIN THE CONTROL CABINET.
- 5. ALL WIRING SHALL BE NEATLY DRESSED AND SUPPORTED.
- 6. FOUNDATION SIZE SHALL BE COORDINATED WITH CABINET SIZE AND MFR.
- 7. DOOR SHALL BE CONSTRUCTED FROM SAME TYPE OF MATERIAL AND THICKNESS AS CABINET.
- 8. DOOR SHALL BE EQUIPPED WITH THREE POINT LATCHING MECHANISM WITH NYLON ROLLERS AT TOP THE BOTTOM.
- 9. DOOR HINGE SHALL BE A HEAVY GAUGE CONTINUOUS HINGE W'TH A 1/4" (6.35 mm) DIA. STAINLESS STEEL HINGE PIN.
- 10. CABINETS SHALL BE PRIMED AND PAINTED AS SPECIFIED.
- 11. ALL CONNECTIONS SHALL BE ABOVE GROUND (NO UNDERGROUND SPLICING)
- 12. REFER TO LANDSCAPE PLANS FOR EXACT LOCATION OF RECEPTACLE ENCLOSURE.
 RECEPTACLES ENCLOSURE SHALL NOT BE INSTALLED ON THE SIDEWALK OR AT GRADE LEVELS CAUSING SAFETY HAZARDS OR OBSTRUCTIONS TO PEDESTRIANS.

	WIRING DIAGE	AM FOR RECEPTACLE CA	BINET FOR	TWO RECEPTACLES	F.A.P. RTE. 347	SECTION 09-00248-00-RS	COUNTY	TOTAL SHEETS	SHEET NO.	
-					011	03 002 10 00 NS	CONTRACT	E17	33432	
	SCALE: 1" = 20'	SHEET NO. 5 OF 29 SHEETS	STA.	TO STA.	ILLINOIS FED. AID PROJECT					

FILE NAME = 219 DIRTE38-sht-light05.dgn

DESIGNED - EE REVISED DRAWN - PY REVISED CHECKED - JB PLOT SCALE = 20.0000 '/ IN. REVISED PLOT DATE = 3/11/2010 DATE REVISED



WIRING DIAGRAM FOR J1 CABINET

FOR THREE OR MORE RECEPTACLES

REFER TO LANDSCAPE PLAN FOR EXACT LOCATION OF CABINET, HANDHOLE, AND RECEPTACLE. FINAL LOCATION TO BE COORDINATED WITH LANDSCAPE ARCHITECT.

ITEM	QUANTITY	MAIN CIRCUIT, 1 POLE, 240 VOLT				
A 1		MAIN CIRCUIT, 1 POLE, 240 VOLT 5AMP,FRAME. 5AMP NON-INTERCHANGEABLE TRIP INTERRUPTING RATING NEMA-22000 AMP. AT 240 VOLT.				
В	1	1.5 KVA, SINGLE PHASE, ENCAPSULATED TRANSFORMER 240X480/120X240 VOLT, 60 HZ. TRIP INTERRUPTING RATING NEMA-22000 AMP. AT 240 VOLT.				
С	2	COPPER GROUND BUS 1/4" X1" X 6" LONG MOUNTED ON PANEL WITH LUGS AND SPARE LUGS				
D	1	BRANCH CIRCUIT, 1 POLE, 120 VOLT 20AMP,FRAME. 20AMP NON-INTERCHANGEABLE TRIP INTERRUPTING RATING NEMA-22000 AMP. AT 120 VOLT.				

LEGEND

Proposed handhole

Proposed vandal proof receptacle (Weatherproof and Ground Fault Interrupter) UL listed, corrosion resistant and cover NEC 406.8.B.2a compliant

- Ground Rod

1. ALL EXTERNAL HARDWARE SHALL BE STAINLESS STEEL.

- 2. THE HEADS OF CONNECTORS SCREWS SHALL BE PAINTED WHITE FOR NEUTRAL BAR CONNECTION AND GREEN FOR GROUND BAR CONNECTORS.
- 3. ALL WIRING WITHIN THE CABINET SHALL BE COLOR CODED AS INDICATED
- R = RED BL = BLUE W = WHITE FOR NEUTRAL B = BLACK Y = YELLOW G = GREEN FOR GROUND
- 4. PROVIDE SEALING GROMMETS FOR ALL OPEN WIRING EXTENDED FROM DEVICES IN BOXES OR CABINETS WITHIN THE CONTROL CABINET.
- 5. ALL WIRING SHALL BE NEATLY DRESSED AND SUPPORTED.
- 6. FOUNDATION SIZE SHALL BE COORDINATED WITH CABINET SIZE AND MFR.

- 7. DOOR SHALL BE CONSTRUCTED FROM SAME TYPE OF MATERIAL AND THICKNESS AS CABINET.
- 8. DOOR SHALL BE EQUIPPED WITH THREE POINT LATCHING MECHANISM WITH NYLON ROLLERS AT TOP THE BOTTOM.
- 9. DOOR HINGE SHALL BE A HEAVY GAUGE CONTINUOUS HINGE WITH A 1/4" (6.35 mm) DIA. STAINLESS STEEL HINGE PIN.
- 10. CABINETS SHALL BE PRIMED AND PAINTED AS SPECIFIED.
- 11. ALL CONNECTIONS SHALL BE ABOVE GROUND (NO UNDERGROUND SPLICING)
- 12. REFER TO LANDSCAPE PLANS FOR EXACT LOCATION OF RECEPTACLE ENCLOSURE.
 RECEPTACLES ENCLOSURE SHALL NOT BE INSTALLED ON THE SIDEWALK OR AT GRADE LEVELS CAUSING SAFETY HAZARDS OR OBSTRUCTIONS TO PEDESTRIANS.



CHICAGO, IL 60654 (312)467-0123


STATE OF ILLINOIS **DEPARTMENT OF TRANSPORTATION**


WIRING	DIAGRAM	FOR	RECEPTACLE	CABINET	FOR	THREE	RECEPTA	ACLE


	F.A.P. RTE.	SECTION		COUNTY	TOTAL	SHEET NO.
•	347	09-00248-00-RS		COOK	274	226
				CONTRACT	NO. 6	3432
		ILLINOIS	FED. AID	PROJECT		-


FILE NAME = ISER NAME = IDOT DESIGNED - EE REVISED REVISED 1RTE38-sht-light06.dgn DRAWN PLOT SCALE = 20.0000 '/ IN. CHECKED - JB REVISED PLOT DATE = 3/11/2010 DATE REVISED


SCALE: 1" = 20' SHEET NO. 6 OF 29 SHEETS STA. TO STA.





















































TERRA 225 W. OHIO ST., FOURTH FL. CHICAGO, IL 60654

(312)467-0123

DESIGNED EE FILE NAME = REVISED DRAWN - PY REVISED 01RTE38-sht-light25.dgn PLOT SCALE = 20.0000 '/ IN. CHECKED - JB REVISED


STATE OF ILLINOIS **DEPARTMENT OF TRANSPORTATION**


	ELECTRIC	AL CABINET	SIGNA	L LINE	DIAGRAM AND LEGEND			F.A.P. RTE.	SECTION	
,			(SHEE	T 3 OF	3)			347	09-00248-00-RS	
ALE:	1" = 20'	SHEET NO. 25	OF 29 S	SHEETS	STA.	T	O STA.		ILLINOIS F	

COUNTY TOTAL SHEET NO.


COOK 274 245

CONTRACT NO. 63432






2) TYPICAL WIRING IN TRENCH DETAIL
N.T.S.



SPLICING ELECTRIC CABLES DETAIL
N.T.S.





HANDHOLE AND POLE TAG ORIENTATION
N.T.S.


LIGHTING POLE, WIRING IN TRENCH, SPLICING ELECTRICAL CABLES AND
HANDHOLE DETAILS


SCALE: 1" = 20' SHEET NO. 26 0F 29 SHEETS STA. TO STA.


| APP | SECTION | COUNTY | TOTAL SHEETS NO. 347 | 09-00248-00-RS | COOK | 274 | 246 | CONTRACT NO. 63432























SECTION A-A



Notes:

- Existing Sanitary or Combined Sewer must be 15" diameter or larger for "dog house" manhole use. Integral pour for base and bench.

- (No precost base)
 All poured—in—place concrete must be 4000 psi non—shrink mix.


 External drop connection must be provided if invert of connecting sewer is 24" or more above the invert of outlet. (See separate MWRD Standard Drop detail.)
- Manhale diameter minimum 60"- increases
- based on the existing sewer diameter.
 Concrete bonding agent must be applied to all interfaces of precost concrete surfaces
- with poured-in-place concrete.


 A curved internal arch form must be used during collar concrete fill. No brick, mortar, or debris is to be used in place of consolidated concrete.

 Debris must not be allowed to enter the
- sewer system at any time during construction. All dimensions noted are minimum allowed. The structure must not be backfilled for a minimum of 24 hours after construction.


"DOG HOUSE" MANHOLE 3 ALTERNATIVE FOR NEW MH CONSTRUCTION ON / CONNECTING TO EXISTING LIVE SEWERS

FILE NAME =	USER NAME = IDOT	DESIGNED - DA	REVISED -				SECTION	COUNTY	TOTAL SHEET SHEETS NO.
D1RTE38-sht-details02.dgn		DRAWN - 5 BM	REVISED -	STATE OF ILLINOIS	PROJECT SPECIFIC DETAILS	347	09-00248-00-RS	соок	274 251
1	PLOT SCALE = 10.00 '/ IN.	CHECKED - JB	REVISED -	DEPARTMENT OF TRANSPORTATION	N my		CONTRACT NO. 634		CT NO. 63432
	PLOT DATE = 3/23/2010	DATE -	REVISED -		SCALE: NTS SHEET NO. OF SHEETS STA. TO STA.		ILLINOIS FED.	AID PROJECT	






TYPICAL ALLEY RETURN




PORTLAND CEMENT CONCRETE SIDEWALK DETAIL


NOTES:

- ONE-HALF INCH THICK EXPANSION JOINTS SHALL BE PLACED BETWEEN THE SIDEWALK AND ALL STRUCTURES SUCH AS LIGHT STANDARDS, TRAFFIC LIGHT STANDARDS, MANHOLES, WHICH EXTEND THROUGH THE SIDEWALK.
- 2. 34" THICK EXPANSION JOINTS SHALL BE PLACED AT INTERVALS OF NOT MORE THAN 100 FEET (30 METERS) IN THE SIDEWALK. WHERE THE SIDEWALK IS CONSTRUCTED ADJACENT-TO PAVEMENT OR CURB HAVING EXPANSION JOINTS. THE EXPANSION JOINTS SHALL ALSO BE PLACED WHERE THE SIDEWALK ABUTS EXISTING SIDEWALKS., BETWEEN DRIVEWAY PAVEMENT AND SIDEWALK, AND BETWEEN SIDEWALK AND CURBS WHERE THE SIDEWALK ABUTS A CURB.



FILE NAME =	USER NAME = IDOT	DESIGNED - DA	REVISED -			F.A.P. SECTION COUNTY TOTAL SHEET
D1RTE38-sht-details03.dgn		DRAWN - BB	REVISED -	STATE OF ILLINOIS	PROJECT SPECIFIC DETAILS	347 09-00248-00-RS COOK 274 252
	PLOT SCALE = 10.00 '/ IN.	CHECKED - JB	REVISED -	DEPARTMENT OF TRANSPORTATION	COLIS NTC CUEET NO OF CHEETS CTA	CONTRACT NO. 63432
	PLOT DATE = 3/11/2010 ~-	DATE -	REVISED -		SCALE: NIS SHEET NO. OF SHEETS STA.	TO STA, ILLINOIS FED. AID PROJECT









FINISH CORNERS WITH EDGER

NOTE: PROVIDE BITUMINOUS PREFORMED JOINT FILLER EVERY 40 MAX., AND AT LOCATIONS SHOWN ON PLANS. — SEE SEALING DETAIL

BAR AS SHOWN ON APPLICATION DETAIL



BITUMINOUS PREFORMED JOINT FILLER (AT PLANTER CURB AND COMBINATION CONCRETE CURB AND GUTTER)



BITUMINOUS PREFORMED JOINT FILLER
(AT PLANTER CURB AND COMBINATION CONCRETE CURB AND GUTTER)

FILE NAME =	USER NAME = IDOT	DESIGNED - BB	REVISED	
DiRTE38-sht-details04.dgn		DRAWN - DA	REVISED -	
	PLOT SCALE = 10.000 '/ IN.	CHECKED - JB	REVISED -	
	PLOT DATE = 3/11/2010 '	DATE -	REVISED -	

HOT POURED

JOINT SEALER

PAVEMENT 1

1/2ªR.


JOINT FILLER


SEALING DETAIL


BITUMINOUS PREFORMED


STATE OF	ILLINOIS	١
DEPARTMENT OF	TRANSPORTATION	ŀ


		DDA	IECT	SPECIFIC	DETAIL		F.A.P. RTE.	SECTION	COUNTY	TOTAL	SHEET NO.
		rnu	JEGI	SPECIFIC	DETAILS		347	09-00248-00-RS	COOK	274	253
SCALE: NTS	SHEET	NO.	OF	SHEETS	STA.	TO STA.		ILLINOIS FED. AI	CONTRACT	NO. 6	53432















DETAIL "A"

LATERAL CONNECTION TO EXISTING SEWER
OF 27" (675) OR SMALLER




<u>DETAIL "B"</u> CLASS SI CONCRETE COLLAR

- O.D. + 12" (300) MIN.

CONSTRUCTION SEQUENCE

- CUT THE EXISTING END OF THE PIPE SO AS TO PRESENT A FLUSH BUTT JOINT. BRUSH AND CLEAN ALL PIPES.
- 2. APPLY THE MASTIC JOINT SEALANT TO THE FIRST 6" (150) OF EACH PIPE.
- 3. BUTT THE PIPES TOGETHER LEAVING A MINIMUM OF 12' × 6' (300 × 150) DEEP EXCAVATION UNDER AND AROUND EACH PIPE END.
- 4. CUT A PIECE OF SHEET METAL GAGE NO. 19 1.1 (0.0418) 18" (450) WIDE BY THE OUTSIDE CIRCUMFERANCE OF THE PIPE PLUS 3" (75) LONG.
- 5. WRAP THE SHEET METAL AROUND THE PIPES, 9" (225) ON EACH SIDE OF THE JOINT, STARTING AT THE TOP OF THE PIPE.
- 6. LAP THE SHEET METAL AT LEAST 3" (75) AT THE TOP OF THE PIPE AND PLACE THE MASTIC JOINT SEALANT BETWEEN THE LAP.
- PLACE TWO METAL BANDS AROUND THE SHEET METAL AND TIGHTEN.
- WIPE OFF ANY EXCESS MASTIC JOINT SEALANT THAT OOZES OUT FROM BETWEEN THE SHEET METAL AND THE PIPES.
- 9. PLACE CLASS SI CONCRETE AROUND THE JOINT.



DETAIL "C"

PROPOSED LATERAL

CONNECTION TO EXISTING SEWER

OF 30" (750) OR LARGER

NOTES

MATERIA

MATERIAL USED FOR THE TEE OR WYE SECTION SHALL BE COMPATIBLE WITH THE EXISTING STORM SEWER OR THE PROPOSED STORM SEWER.

CONSTRUCTION METHODS

- I. THIS WORK SHALL BE CONSTRUCTED IN CONFORMANCE WITH THE APPLICABLE PORTIONS OF SECTION 550 OF THE STANDARD SPECIFICATIONS.
- II. CONNECTION TO AN EXISTING STORM SEWER SHALL BE BY EITHER OF THE FOLLOWING METHODS: A) PROPOSED STORM SEWER CONNECTION TO EXISTING SEWER OF 27" (675) OR SMALLER SEE DETAIL "A" AND "B".
 - B) PROPOSED STORM SEWER CONNECTION TO EXISTING SEWER OF 30" (750) OR LARGER SEE DETAIL "C".

IF THE EXISTING SEWER PIPE IS CRACKED, BROKEN OR OTHERWISE DAMAGED BY THE CONTRACTOR IN MAKING THE CIRCULAR OPENING, THE CONTRACTOR SHALL REPLACE THAT SECTION OF PIPE WITH PIPE EQUAL AND SIMILAR IN ALL RESPECTS TO THE PIPE IN THE EXISTING SEWER, IN A CAREFUL WORKMANLIKE MANNER, WITHOUT EXTRA COMPENSATION.

GENERAL

CARE MUST BE TAKEN TO PREVENT DEBRIS FROM ENTERING THE SEWER.
ALL DEBRIS WHICH ENTERS THE SEWER MUST BE REMOVED. THE SEWER MUST
BE LEFT CLEAN AND UNOBSTRUCTED UPON COMPLETION OF THE CONTRACT.

CARE MUST BE TAKEN TO PREVENT ANY PART OF THE NEW PIPE CONNECTION FROM PROJECTING INTO THE EXISTING SEWER.

BASIS OF PAYMENT

TEE OR WYE CONNECTIONS SHALL BE PAID FOR AT THE CONTRACT UNIT PRICE EACH FOR STORM SEWER TEE OR WYE OF THE TYPE AND SIZE SPECIFIED IN THE PLANS, THIS PRICE SHALL INCLUDE ALL EXCAVATION OF THE TRENCH, REMOVAL OF THE EXISTING STORM SEWER, FURNISHING AND INSTALLING THE REQUIRED CONCRETE COLLAR, AND ALL OTHER MATERIAL NECESSARY TO COMPLETE THIS WORK AS SHOWN AND SPECIFIED.


REMOVAL AND REINSTALLATION OF EXISTING STORM SEWER ADJACENT TO THE PROPOSED TEE OR WYE SECTION, FOR THE PURPOSE OF FACILITATING THE INSTALLATION OF THE TEE OR WYE SECTION, WILL NOT BE PAID FOR SEPARATELY BUT SHALL BE INCLUDED IN THE UNIT PRICE BID FOR THE WORK.

TRENCH BACKFILL, EXCAVATION IN ROCK AND REMOVAL AND REPLACEMENT OF UNSUITABLE MATERIAL BELOW PLAN BEDDING GRADE WILL BE PAID FOR SEPARATELY.

CONCRETE COLLAR FOR CONNECTING A PROPOSED STORM SEWER TO AN EXISTING STORM SEWER WILL NOT BE PAID PAID FOR SEPARATELY BUT SHALL BE INCLUDED IN THE COST OF THE PROPOSED STORM SEWER.

ALL DIMENSIONS ARE IN INCHES (MILLIMETERS) UNLESS OTHERWISE SHOWN.

FILE NAME =	USER NAME = gagl:anobt	DESIGNED - M. DE YONG	REVISED - M. DE YONG 05-08-92		l y i	DETAIL OF STORM SEWER	F.A.P. RTE.	SECTION	COUNTY	TOTAL SHEET
W:\dietetd\22x34\bd07.dgn	PLOT SCALE = 50.000 '/ IN.	CHECKED -	REVISED - R. SHAH 09-09-94 REVISED - R. SHAH 10-25-94	STATE OF ILLINOIS DEPARTMENT OF TRANSPORTATION	CONNECTION TO EXISTING SEWER			09-00248-00-RS BD500-01 (BD-7)	COOK	274 259
	PLOT DATE = 1/4/2008	DATE - 07-25-90	REVISED - R. SHAH 06-12-96		SCALE: NONE	SHEET NO. 1 OF 1 SHEETS STA. TO STA.		AD DIST. NO. 1 ILLINOIS FED. A	CONTRACT D PROJECT	NO.



CITY OF CHICAGO CASTINGS ARE THE PROPERTY OF THE CITY AND THE CONTRACTOR SHALL NOTIFY THE CITY FOR REMOVAL AND DISPOSITION OF THE CASTINGS.

THE METAL PLATE USED TO COVER THE STRUCTURE SHALL REMAIN THE PROPERTY OF THE CONTRACTOR.

WHEN STRUCTURES ARE TO BE ADJUSTED OR RECONSTRUCTED. THE LOWERING AND RAISING OF THE FRAMES AND LIDS WILL NOT BE PAID FOR SEPARATELY BUT WILL BE INCLUDED IN THE COST OF THE CORRESPONDING PAY ITEM.

CONSTRUCTION PROCEDURES

STAGE 1 (BEFORE PAVEMENT MILLING)

- A) REMOVE A MINIMUM OF 12 (300) OF THE PAVEMENT FROM AROUND THE STRUCTURE.
- B) REMOVE THE EXISTING FRAME AND LID FROM THE STRUCTURE.
- C) COVER THE STRUCTURE OPENING WITH A 36 (900) DIAMETER METAL PLATE.
- D) BACKFILL WITH CRUSHED STONE AND A MINIMUM $1^{\prime}\!/_{2}$ (40) THICK HMA SURFACE MIX APPROVED BY THE ENGINEER.

STAGE 2 (AFTER PAVEMENT MILLING)

- A) REMOVE THE HMA SURFACE MIX AND CRUSHED STONE.
- B) INSTALL THE FRAME AND LID; ADJUST THE FRAME TO ITS FINAL SURFACE ELEVATION.
- C) THE SURROUNDING SPACE SHALL BE FILLED WITH CLASS SI CONCRETE, OR HMA SURFACE COURSE OR HMA BINDER COURSE TO THE ELEVATION OF THE SURFACE OF THE EXISTING BASE COURSE OR THE BINDER COURSE.

THE PROCEDURE EXPLAINED ABOVE SHALL CONFORM TO THE APPLICABLE PORTIONS OF SECTIONS 353, 406, 602, AND 603 OF THE STANDARD SPECIFICATIONS.

LEGEND

- 1 SUB-BASE GRANULAR MATERIAL
- 6 FRAME AND LID (SEE NOTES)
- 2 EXISTING PAVEMENT
- CLASS SI CONCRETE, HMA SURFACE COURSE OR HMA BINDER COURSE
- 3 36 (900) DIAMETER METAL PLATE
- 8 PROPOSED HMA SURFACE COURSE
- PROPOSED CRUSHED STONE AND HMA SURFACE MIX 5 EXISTING STRUCTURE
- 9 PROPOSED HMA BINDER COURSE

LOCATION OF STRUCTURES:

THE CONTRACTOR WILL BE REQUIRED TO KEEP A RECORD OF THE LOCATIONS OF THE BURIED STRUCTURES ACCORDING TO THE STATION AND DISTANCE LEFT OR RIGHT OF THE CENTERLINE OF PAVEMENT. UPON COMPLETION OF THE WORK. THE CONTRACTOR WILL DELIVER THE RECORD TO THE ENGINEER.

BASIS OF PAYMENT: THIS WORK WILL BE PAID FOR AT THE CONTRACT UNIT PRICE PER EACH FOR "FRAMES AND LIDS TO BE ADJUSTED, SPECIAL" NEW FRAMES AND LIDS, WHEN SPECIFIED, WILL BE PAID FOR SEPARATELY.


DETAILS FOR FRAMES AND LIDS ADJUSTMENT WITH MILLING


> ALL DIMENSIONS ARE IN INCHES (MILLIMETERS) UNLESS OTHERWISE SHOWN

> > COUNTY TOTAL SHEET NO.

CONTRACT NO.

DESIGNED - R. SHAH REVISED - R. SHAH 03-10-95 JSER NAME = gaglianobt FILE NAME = SECTION DETAILS FOR STATE OF ILLINOIS REVISED - A. ABBAS 03-21-97 Wi\distatd\22x34\bd08.dgn FRAMES AND LIDS ADJUSTMENT WITH MILLING **DEPARTMENT OF TRANSPORTATION** PLOT SCALE = 50.0000 ' / IN. CHECKED REVISED - R. WIEDEMAN 05-14-04 BD600-03 (BD-8) CONTR.
FED. ROAD DIST. NO. 1 ILLINOIS FED. AID PROJECT DATE - 10-25-94 SCALE: NONE SHEET NO. 1 OF 1 SHEETS STA. PLOT DATE = 1/4/2008 REVISED - R. BORO 01-01-07





NOTES:

- 1. THE WIDTH OF THE FULL DEPTH PATCH OVER A TRENCH SHALL BE 12 (300) WIDER ON EACH SIDE OF THE TRENCH.
- 2. FOR METHOD OF MEASUREMENT AND BASIS OF PAYMENT, SEE RECURRING SPECIAL PROVISION "PATCHING WITH HOT-MIX ASPHALT OVERLAY REMOVAL".

SEQUENCE OF CONSTRUCTION (PATCHING FIRST)


- 1. REMOVE THE EXISTING HMA MATERIAL OVER THE AREA TO BE PATCHED.
- 2. REMOVE AND REPLACE WITH CLASS C OR D PATCH.
- 3. REPLACE HMA MATERIAL OVER THE AREA TO BE PATCHED.

SEQUENCE OF CONSTRUCTION (MILLING FIRST)


- 1. MILL HMA FIRST IF THERE IS AT LEAST 41/2 INCHES OR MORE OF HMA MATERIAL ON TOP OF THE EXISTING PAVEMENT OR IF THE PAVEMENT IS FULL DEPTH HMA. A MINIMUM OF 2 INCHES OF HMA MATERIAL SHALL BE IN PLACE AFTER MILLING.
- 2. REMOVE AND REPLACE WITH FULL DEPTH CLASS D PATCHES TO TOP OF MILLED SURFACE.

ALL DIMENSIONS ARE IN INCHES (MILLIMETERS) UNLESS OTHERWISE SHOWN.

	SECTION	COUNTY TOTAL SHEET
Ct/projects/distatd22x34\bd22.dgn DRAWN - REVISED - R. BORO 01-01-07 STATE OF ILLINOIS	347 09-00248-00-RS	COOK 274 262
PLOT SCALE = 50.000 '/ IN. CHECKED - R. BORO 09-04-07 DEPARTMENT OF TRANSPORTATION HMA SURFACED PAVEMENT	BD400-04 (BD-22)	CONTRACT NO.
PLOT DATE = 18/27/2808 DATE - 10-25-94 REVISED - K. ENG 10-27-08 SCALE; NONE SHEET NO. 1 OF 1 SHEETS STA. TO STA. FE		ID PROJECT




OPTION 1



(FOR BUTT JOINT AND HMA TAPER SEE DETAIL BELOW)

OPTION 2

TYPICAL TEMPORARY RAMP




TYPICAL BUTT JOINT AND HMA TAPER FOR MILLING AND RESURFACING


DESIGNED - M. DE YONG USER NAME = gaglianobt REVISED - R. SHAH 10-25-94 DRAWN REVISED - A. ABBAS 03-21-97 W:\diststd\22x34\bd32.dgn PLOT SCALE = 50.0000 '/ IN. CHECKED -REVISED - M. GOMEZ 04-06-01 PLOT DATE = 1/4/2008 DATE - 06-13-90 REVISED - R. BORO 01-01-07

FILE NAME =

STATE OF ILLINOIS **DEPARTMENT OF TRANSPORTATION**

COUNTY TOTAL SHEE SHEETS NO. **BUTT JOINT AND** HMA TAPER DETAILS BD400-05 BD32 CONTRACT NO. SHEET NO. 1 OF 1 SHEETS STA. SCALE: NONE TO STA.





TYPICAL BUTT JOINT AND HMA TAPER FOR RESURFACING ONLY


* * PC CONCRETE, HMA OR HMA RESURFACED PAVEMENT.

- A: MAINLINE ROADWAYS AND MAJOR SIDE ROADS.
- B: MINOR SIDE ROADS.
- C: THE TEMP. RAMP SHALL BE CONSTRUCTED IMMEDIATELY UPON REMOVAL OF THE EXISTING HMA SURFACE.
- D: THE BUTT JOINT SHALL BE CONSTRUCTED IMMEDIATELY PRIOR TO PLACING THE PROPOSED HMA COURSES.
- E: TAPER THE TEMP. RAMP AT A RATE OF 3'-0" (900 mm) PER 1 INCH (25 mm) OF MILLING THICKNESS.
- F: INSTALLATION AND REMOVAL OF THE 4'-6" (1.35 m) TEMP. RAMP IS INCLUDED IN COST OF HMA SURFACE REMOVAL - BUTT JOINT
- G: SEE ARTICLE 406.08 AND 406.14 OF THE STANDARD SPECIFICATIONS FOR "HMA AND/OR PCC SURFACE REMOVAL, BUTT JOINT".
- * SEE TYPICAL SECTIONS FOR MILLING THICKNESS.
- * * * 20'-0" (6.1 m) PER 1 (25) RESURFACING (NOTE "A") 10'-0" (3.0 m) PER 1 (25) RESURFACING (NOTE "B")

BASIS OF PAYMENT:

THE BUTT JOINT WILL BE PAID FOR AT THE CONTRACT UNIT PRICE PER SOUARE YARD (SOUARE METER) FOR "HOIT-MIX ASPHALT SURFACE REMOVAL - BUTT JOINT" OR FOR "PORTLAND CEMENT CONCRETE SURFACE REMOVAL- BUTT JOINT".

ALL DIMENSIONS ARE IN INCHES (MILLIMETERS) UNLESS OTHERWISE SHOWN.



HMA TAPER AT EDGE OF P.C.C PAVEMENT


HMA SURF ACE		LEVELING BINDER	
MIX	THICKNESS	THICKNESS	* MILLING AT GUTTER FLAG
C OR D	11/2 (38)	1 (25)	11/4 (33)
F	1¾ (44)	¾ (19)	11/2 (38)

ALL DIMENSIONS ARE IN INCHES (MILLIMETERS) UNLESS OTHERWISE SHOWN.

FILE NAME =	USER NAME = geglianobt	DESIGNED -	R. SHAH	REVISED -	R. SHAH 10-25-94
W:\diststd\22x34\bd33.dgn		DRAWN -	JIS	REVISED -	A. ABBAS 05-05-99
	PLOT SCALE = 50.0000 '/ IN.	CHECKED -	A. ABBAS	REVISED -	E. GOMEZ 12-21-00
	PLOT DATE = 1/4/2008	DATE -	09-10-94	REVISED -	R. BORO 01-01-07

STATE OF ILLINOIS
DEPARTMENT OF TRANSPORTATION

	HMA TAPER	F.A.P. SECTION		COUNTY	TOTAL	SHEET NO.		
2	EDGE OF P.C.C. PA	VEMENT		347	09-00248-00-RS	COOK	274	264
SCALE: NONE	SHEET NO. 1 OF 1 SHEETS	STA.	TO STA.		D400-06 (BD33)	CONTRACT	NO.	
SCALE: NONE	SHEET NO. 1 OF 1 SHEETS	JIM.	10 31A.	FED. RO	AD DIST. NO. 1 ILLINOIS FED. A	ID PROJECT		



SEQUENCE OF CONSTRUCTION:


- 1. CLOSE EXISTING VALVE.
- 2. REMOVE EXISTING HYDRANT.
- 3. INSTALL HYDRANT EXTENSION AND NEW VALVE.
- 4. RELOCATE EXISTING HYDRANT.
- 5. OPEN EXISTING VALVE, REMOVE BOX.
- 6. BACKFILL.
- 7. FLUSH AND TEST FOR CHLORIDE RESIDUAL AND PROVIDE TEST.


ALL WORK TO BE DONE IN ACCORDANCE WITH ARTICLE 564 OF THE STANDARD SPECIFICATIONS. NEW VALVE AND BOX SHALL BE SAME MAKE AND MODEL AS EXISTING.

FIRE HYDRANT TO BE MOVED

ALL DIMENSIONS ARE IN INCHES (MILLIMETERS) UNLESS OTHERWISE SHOWN.

l	FILE NAME =	USER NAME = gaglianobt 5	DESIGNED -	REVISED - R. SHAH 09-09-94		FIRE HYDRANT TO BE MOVED	F.A.P. SECTION	COUNTY TOTAL SHEET
	W:\diststd\22x34\bd36.dgn		DRAWN -	REVISED - R. SHAH 10-25-94	STATE OF ILLINOIS	FINE HIDNAMI TO DE MOYED	347 09-00248-00-RS	COUNTY SHEETS NO.
		PLOT SCALE = 50.0000 '/ IN.	CHECKED -	REVISED -	DEPARTMENT OF TRANSPORTATION		BD-36	CONTRACT NO.
		PLOT DATE = 1/4/2008	DATE -	REVISED -		SCALE: NONE SHEET NO. 1 OF 1 SHEETS STA. TO STA.		D PROJECT





FILE

PANEL EQUIPMENT

		BILL OF MATERIAL
ITEM	QUANTITY	DESCRIPTION
А	1	MAIN CIRCUIT BREAKER, 2 POLE, 600 VOLT 100 AMP. FRAME, 100 AMP. NON-INTERCHANGEABLE TRIP INTERRUPTING RATING NEMA-22000 AMP. AT 480 VOLT.
В	1	REMOTE CONTROL SWITCH, ELECTRICALLY OPERATED, MECHANICALLY HELD, 2 POLE, SINGLE THROW, 100 AMP., 600 VOLTS CONTROL CIRCUIT 240 VOLT.
С	8	CIRCUIT BREAKERS, 1 POLE, 100AMP. FRAME . 50 AMP. NON-INTERCHANGEABLE TRIP INTERRUPTING RATING NEMA-10,000 AMP. AT 240 V.
D	2	CONTROL CIRCUIT-CIRCUIT BREAKER. 1 POLE, 240 V., 100 AMP. FRAME, 15 AMP. NON-INTERCHANGEABLE TRIP INTERRUPTING RATING NEMA-5000 AMP. AT 240 V.
E	1	ASTRONOMIC MICROPROCESSOR-BASED 2-CHANNEL CONTROLLER [TIME SWITCH].
F	1	20 A., 120 V. FUSE.
G	1	1.5 KVA, SINGLE PHASE, ENCAPSULATED TRANSFORMER 240 X 480 / 120 X 240 VOLT, 60 Hz.
н	1	SPST 20A SWITCH ON DOOR, TO TURN LIGHT ON WHEN DOOR IS OPEN,
I	1	INCANDESCENT LIGHTING FIXTURE ENCLOSED AND GASKETED WITH 60 WATT, 120 V. LAMP.
J	1	20 A., 120 V., DUPLEX RECEPTACLE, GFCI.
к	1	COPPER GROUND BUS $1/4$ " (6.35) X 1" (25.4) X 12" (304.8 mm) LONG MOUNTED ON PANEL WITH LUGS AND 4 SPARE LUGS
L	1	TOGGLE SWITCHES MOUNTED IN 4" (101.6) X 4" (101.6 mm) BOX
М	1	COPPER GROUND BUS 1/4" (6.35) X 1" (25.4) X 12" (304.8 mm) LONG MOUNTED ON PANEL WITH LUGS AND SPARE LUGS

- 1. ALL DIMENSIONS ARE IN INCHES (MILLIMETERS) UNLESS OTHERWISE SHOWN.
- 2. FOUNDATION SIZE SHALL BE COORDINATED WITH CABINET SIZE AND MFR.
- 3. IN FRONT OF CONTROL CABINET DOOR, REMOVE VEGETATION AND 2" (50.8 mm) TOP SOIL, LEVEL THE 12. ALL WIRING WITHIN THE CABINET SHALL BE TO CONTROL CABINET, A CONCRETE PAD 36" (914,4 mm) \times 60" (18,288 m) \times 4" (101 mm) MIN. SIZE. THE COST OF LABOR AND MATERIALS ARE INCLUDED IN THE COST OF THE CONTROLLER.
- DOOR SHALL BE CONSTRUCTED FROM SAME TYPE OF MATERIAL AND THICKNESS AS CABINET.
- 5. DOOR SHALL BE EQUIPPED WITH THREE POINT LATCHING MECHANISM WITH NYLON ROLLERS AT TOP THE BOTTOM.
- 6. DOOR HINGE SHALL BE A HEAVY GAUGE CONTINUOUS HINGE WITH A 1/4" (6.35 mm)
 DIA. STAINLESS STEEL HINGE PIN.
- 7. ALL EXTERNAL HARDWARE SHALL BE STAINLESS STEEL.
- 8. CONTROL WIRING TO BE #12 AWG, 600V, TYPE "SIS" GRAY SWITCH BOARD WIRE, STRANDED
- 9. METER BOX SHALL BE MOUNTED ON THE SIDE OF CONTROL CABINET, NEAR TO THE SERVICE POLE.

- 10. CABINETS SHALL BE PRIMED AND PAINTED AS SPECIFIED.
- 11. THE HEADS OF CONNECTORS SCREWS SHALL BE PAINTED WHITE FOR NEUTRAL BAR CONNECTION AND GREEN FOR GROUND
- COLOR CODED AS INDICATED.

 R = RED BL = BLUE W = WHITE B = BLACK Y = YELLOW
- 13. PROVIDE SEALING GROMMETS FOR ALL OPEN WIRING EXTENDED FROM DEVICES IN BOXES OR CABINETS WITHIN THE CONTROL CABINET.
- 14. ALL WIRING SHALL BE NEATLY DRESSED AND SUPPORTED.
- 15. THE CONTROLLER SHALL BE CONSTRUCTED TO U.L. STD. 508 AND BEAR THE U.L. LABEL "ENCLOSED INDUSTRIAL CONTROL PANEL".
- 16. 12" (304.8) X-16" (406.4 mm) STAINLESS STEEL EXTERIOR NAMEPLATE SHALL BE ENGRAVED TO "STATE OF ILLINOIS LIGHTING CONTROLS" UNLESS OTHERWISE SPECIFIED.

:\diststd\22x34\be215.dgn DRA	AWAI _ C	35.4650					SECTION	COUNTY CULAL SHEET
		REVISED -	STATE OF ILLINOIS		LIGHTING CONTROLLER SINGLE DOOR	347	09-00248-00-RS	COOK 274 266
PLOT SCALE = 50.0000 '/ IN. CHE PLOT DATE = 1/4/2008 DAT	ECKED -	REVISED -	DEPARTMENT OF TRANSPORTATION	SCALE: NONE	SHEET NO. 1 OF 1 SHEETS STA. TO STA.	FED. ROAD DI	BE-215 ST. NO. 1 ILLINOIS FED. AID I	CONTRACT NO.

LIGHT POLE FOUNDATION DEPTH TABLE 30 FT. (9.144 m) TO 35 FT. (10.668 m) MOUNTING HEIGHT

132177 1117 10 33	1 12 (102000 1	117 1000141 1140
SOIL CONDITIONS	DESIGN DEPTH "	" OF FOUNDATION
SOIL CONDITIONS	SINGLE ARM POLE	TWIN ARM POLE
SOFT CLAY	11'-0''	12'-8"
Ou = 0.375 TON/SQ. FT.	(3.35 m)	(3.85 m)
MEDIUM CLAY	9'-0"	14'-10"
Qu = 0.75 TON/SQ.FT	(2.74 m)	(4.52 m)
STIFF CLAY	7'-6"	8'-7"
Qu = 1.50 TON/SQ. FT.	(2.29 m)	(2.61 m)
LOOSE SAND	9'-6"	10'-7"
Ø = 34°	(2.90 m)	(3,22 m)
MEDIUM SAND	9'-0"	9'-10"
Ø = 37.5°	(2.74 m)	(2,99 m)
DENSE SAND	8'-3"	9'-7"
Ø = 40°	(2.51 m)	(2.91 m)

6" (152.4) THREADED

%" T. X 4" DIA. WASHER, TACK WELDED


ANCHOR BOLT DETAIL

60" (1500)


FOUNDATION EXTENSION DETAIL


TOP OF ANCHOR ROD

4" (100) MAX.



TOP VIEW





SECTION A-A

	'			
FILE NAME =	USER NAME = gaglianobt	DESIGNED -	REVISED -	Γ
Wi\diststd\22x34\be300.dgn		DRAWN -	REVISED	
	PLOT SCALE = 50.0000 '/ IN	CHECKED -	REVISED -	
	PLOT DATE = 1/4/2008	DATE -	PEVISED	


GROUND LINE


STATE OF ILLINOIS DEPARTMENT OF TRANSPORTATION

LIGHT POLE FOUNDATION	F.A.P.	SECTION	COUNTY	TOTAL	SHEET NO.
30' (9.144 m) TO 35' (10.668 m) M.H. 11 1/2" (292 mm) BOLT CIRCLE	347	09-00248-00-RS	COOK	274	267
	FFD. RO	BE-300 AD DIST. NO. 1 ILLINOIS FED. A	CONTRACT	NO.	

<u>NOTES</u>

- 1. ALL DIMENSIONS ARE IN INCHES (MILLIMETERS) UNLESS OTHERWISE SHOWN.
- THE ANCHOR RODS AND RACEWAYS SHALL BE PROPERLY SECURED IN PLACE BEFORE THE CONCRETE IN PLACED.
- 3. THE FOUNDATION SHALL NOT PROTRUDE MORE THAN 4 IN. (100 mm) ABOVE THE FINISHED GRADE WITHIN A 60 IN. (1,5 m) CHORD ACROSS THE FOUNDATION, WITH ANCHOR RODS INCLUDED, IN ACCORDANCE WITH AASHTO GUIDELINES, IF THE FOUNDATION HEIGHT, INCLUDING ANCHOR RODS, EXTENDS BEYOND THESE SPECIFIED LIMITS, THE FOUNDATION SHALL BE REPLACED AT THE CONTRACTOR'S EXPENSE. SEE FOUNDATION EXTENSION DETAIL.
- 4. THE HOLE FOR THE FOUNDATION SHALL BE MADE BY ORILLING WITH AN AUGER, OF THE SAME DIAMETER AS THE FOUNDATION. IF SOIL CONDITIONS REQUIRE THE USE OF A LINER TO FORM THE HOLE, THE LINER SHALL BE WITHDRAWN AS THE CONCRETE IS DEPOSITED.
- 5. THE TOP OF THE FOUNDATION SHALL BE CONSTRUCTED LEVEL. A LINER OR FORM SHALL BE USED TO PRODUCE A UNIFORM SMOOTH SIDE TO THE TOP OF THE FOUNDATION. FOUNDATION TOP SHALL BE CHAMFERED 34-IN. (20 mm).
- THE CONCRETE SHALL BE CLASS SI. CONCRETE SHALL CURE ACCORDING TO ARTICLE 1020,13 BEFORE LIGHT POLES ARE INSTALLED.
- 7. THE ANCHOR ROD SHALL BE A HOOK ROD TYPE, COLD BENDING OF THE ANCHOR ROD WILL NOT BE ALLOWED. THE RADIUS OF THE HOOK BEND SHALL NOT BE LESS THAN 4 TIMES THE NOMINAL DIAMETER OF THE ANCHOR ROD. A TACK WELDED ANCHOR ROD MAY BE SUBSTITUTED WITH THE APPROVAL OF THE ENGINEER.
- B. THE ANCHOR RODS SHALL BE ACCORDING TO ASTM F1554 GRADE 725 (GRADE 105). NUTS SHALL BE HEXAGON NUTS ACCORDING TO ASTM A 194 2H OR ASTM A 563 DH, AND WASHERS SHALL BE ACCORDING TO ASTM F 436.
- 9. ANCHOR RODS, NUTS AND WASHERS SHALL BE COMPLETELY GALVANIZED BY EITHER THE HOT-DIPPED PROCESS CONFORMING WITH AASHTO M 232, THE MECHANICAL PLATING METHOD CONFORMING TO AASHTO M 298, CLASS 50 WITH A MAXIMUM COATING THICKNESS OF 150 UM/6 MILS) OR THE ELECTROLYTIC PROCESS ACCORDING TO ASTM F 1136.
- 10. THE ANCHOR RODS SHALL BE THREADED A MINIMUM OF 6 INCHES (150 mm) WITH A MINIMUM OF 3 INCHES (75 mm) OF THREADED ANCHOR ROD EMBEDDED IN THE FOUNDATION.
- 11. ANCHOR RODS SHALL PROJECT 2¾" (69.9 mm) ABOVE THE TOP OF THE FOUNDATION. IF BREAKAWAY COUPLINGS ARE SPECIFIED, THE CONTRACTOR SHALL CAREFULLY COORDINATE THE ANCHOR ROD PROJECTION WITH THE INSTALLATION REQUIREMENTS OF THE BREAKAWAY COUPLINGS.
- 12. THE CONTRACTOR SHALL USE A *3 SPIRAL AT 6" (152.4 mm) PITCH OR MAY SUBSTITUTE *3 TIES AT 12" (304.8 mm) O.C. WITH THE APPROVAL OF THE ENGINEER.
- 13. THE CABLE TRENCHES AND FOUNDATION SHALL BE BACK FILLED AND COMPACTED AS SPECIFIED BEFORE THE LIGHT POLE IS ERECTED.
- 14. THE RACEWAYS SHALL PROJECT 1" (25.4 mm) ABOVE THE TOP OF THE FOUNDATION.





HELIX FOUNDATION SIZE

POLE MOUNTING HEIGHT	BOLT CIRCLE	SHAFT DIAMETER	SHAFT LENGTH	BASEPLATE
30 FT.	111/2"	85/8′′	6 FT.	12"x12"x1"
31 FT35 FT.	111/2"	85/8''	6 FT.	12"x12"x1"
36 FT40FT.	15"	85/8′′	6 FT.	15"×15"×1 ¹ / ₄ "
41 FT45 FT.	15"	85/8''	6 FT.	15"×15"×11/4"
46 FT50 FT.	15''	10"	8 FT.	15"×15"×11/4"

METAL HELIX FOUNDATION MATERIALS


ITEM	MATERIAL REQUIREMENT
BASERLATE	AASHTO M 270M, GRADE 36 (M270M, GRADE 250)
SHAFT	ASTM A 252, GRADE 2 (PHOSPHOROUS 0.04% MAXIMUM, SULFUR 0.05% MAXIMUM)
HELIX SCREW	AASHTO M 183 (ASTM A 635)
PILOT POINT	AASHTO M 270 (ASTM A 575)
ANCHOR RODS/STUDS	AASHTO M 314 (ASTM F 1554)
HEXAGON NUTS	AASHTO M 291M (ASTM A 563) GRADE DH, OR AASHTO M 292 (ASTM A 194) GRADE 2H
WASHERS	AASHTO M 293 (ASTM F 436)

SEE NOTE NO. 6 1" (25,4) MIN. CLEARANCE -0.25" WALL, MIN. SHAFT DIA. 11/4" (31.75) DIA.

NOTES:


- 1. ALL DIMENSION IN INCHES (MILLIMETERS) UNLESS OTHERWISE SHOWN.
- 2. ALL MATERIAL SHALL BE GALVINIZED ACCORDING TO AASHTO M111, UNLESS OTHERWISE SPECIFIED.
- 3. ALL WELDS SHALL BE CONTINUOUS AND NOT LESS THAN 1/4" (6.35 mm) FILLET WELDS. THE WELDED FOUNDATION SHALL BE CAPABLE OF WITHSTANDING 10,000 FT/LBS (13558.18 n.m) OF INSTALLATION TORQUE APPLIED ABOUT THE AXIS OF THE FOUNDATION.
- 4. THE HELIX FOUNDATION SHAFT SHALL BE INSTALLED VERTICAL AND THE BASE PLATE SHALL BE IN LEVEL. THE BREAKAWAY COUPLINGS AND HARDWARE SHALL NOT BE USED TO ALIGN THE POLE INSTALLATION.
- 5. THE CABLE TRENCH SHALL BE BACKFILLED AND FIRMLY COMPACTED BEFORE THE INSTALLATION OF THE LIGHT POLE.
- 6. THE CONTRACTOR SHALL COORDINATE EXTENSION OF ANCHOR BOLTS ABOVE TOP OF THE BASE PLATE WITH THE BREAKAWAY DEVICE MANUFACTURER'S REQUIREMENTS.
- 7. ANY VOIDS WITHIN THE METAL FOUNDATION SHALL BE FILLED WITH FINE AGGREGATE.
- 8. METAL FOUNDATIONS SHALL BE INSTALLED IN UNDISTURBED SOIL. PREDRILLING A PILOT HOLE AND/OR BACKFILLING AROUND THE FOUNDTION IS NOT ALLOWED.
- 9. THE METAL FOUNDATION SHALL NOT BE INSTALLED TO A TORQUE WHICH EXCEEDS THE MANUFACTURER'S MAXIMUM TORQUE RATING NOR SHALL IT BE INSTALLED TO AN INSTALLATION TORQUE VALUE OF LESS THAN 3,500 FT LB (4,750 KNM). METAL FOUNDATIONS THAT ARE NOT INSTALLED TO FULL INSTALLATION DEPTH OR DO NOT ACHIEVE THE MINIMUM INSTALLATION TORQUE SHALL BE REMOVED AND REPLACED WITH A CONCRETE FOUNDATION AT NO ADDITIONAL COST.
- 10. THE BASEPLATE SHALL BE PERPENDICULAR TO THE SHAFT AXIS (± 1°) AND THE HOLE CENTERLINE SHALL BE CONCENTRIC (± 0.188) TO THE SHAFT AXIS.
- 11. THE PILOT POINT AND SHAFT AXIS SHALL BE CONCENTRIC (± 0.125) AND IN LINE (± 2°).
- 12. THE BASEPLATE SHALL BE STAMPED WITH THE MANUFACTURERS NAME AND DATE OF MANUFACTURE.

								3		
FILE NAME =	USER NAME = gaglianobt	DESIGNED -	REVISED -		LIGHT POLE FOUNDATION, METAL	F.A.P.	SECTION	COUNTY	TOTAL	SHEET
W:\d:ststd\22x34\be305.dgn		DRAWN - DLB	REVISED -	STATE OF ILLINOIS	LIGHT FOLE FOORDATION, METAL	347	09-00248-00-RS	COOK	SHEETS	NU.
	PLOT SCALE = 50.000 '/ IN.	CHECKED -	REVISED -	DEPARTMENT OF TRANSPORTATION		1	BE-305	CONTRACT	T NO	268
1	PLOT DATE = 1/4/2008	DATE - 02-27-07	REVISED -		SCALE: NONE SHEET NO. 1 OF 1 SHEETS STA. TO STA.	FFD. RC	DAD DIST NO 1 JULINOIS FED AL		· NO	



TYPICAL SPLICE DETAIL

N.T.S.



POLE WIRING DETAIL

N.T.S.

FILE NAME =	USER NAME = gaglianobt	DESIGNED -	REVISED - 08-08-03		MISC. ELECTRICAL DETAILS	F.A.P. SECTION	COUNTY TOTAL S	SHEE
Wi\diststd\22x34\be702.dgn		DRAWN -	REVISED -	STATE OF ILLINOIS		347 09 00248 00 DC	SHEETS	NO.
	PLOT SCALE = 50.000 '/ IN.	CHECKED -	REVISED -	DEPARTMENT OF TRANSPORTATION	SHEET A	BE-702	CONTRACT NO.	269
i	PLOT DATE = 1/4/2008	DATE -	REVISED -		SCALE: NONE SHEET NO. 1 OF 1 SHEETS STA. TO STA.	FED. ROAD DIST, NO. 1 ILLINOIS FEE		
					*************************************		T THE THOOLEST	

12" (305) MAXIMUM WIDTH EXCEPT AS APPROVED BY THE ENGINEER

12" (305)

- WARNING TAPE AS SPECIFIED


UNIT DUCT OR OTHER RACEWAY
AND WIRING AS PER PLANS. COMPLETE

WITH INTERNAL INSULATED EQUIPMENT GROUND WIRE.

TYPICAL WIRING IN TRENCH DETAIL

N.T.S.

30" (762) MINIMUM COVER



TRAFFIC CONTROL AND PROTECTION FOR SIDE ROADS, INTERSECTIONS, AND DRIVEWAYS

NOTES:

- A. FOR NO LANE RESTRICTION ON THE SIDE ROAD OR DRIVEWAYS
- SIDE ROAD WITH A SPEED LIMIT OF 40 MPH (60 km/h) OR LESS AS SHOWN ON THE DRAWING AND AS DIRECTED BY THE ENGINEER:
- O) ONE ROAD CONSTRUCTION AHEAD SIGN 36 x 36 (900x900) WITH A FLASHER AND FLAG MOUNTED ON IT APPROXIMATELY 200' (60 m) IN ADVANCE OF THE MAIN ROUTE.
- b) THE CLOSED PORTION OF THE MAIN ROUTE SHALL BE PROTECTED BY BLOCKING WITH TYPE I, TYPE II OR TYPE III BARRICADES, 1/3 OF THE CROSS SECTION OF THE CLOSED PORTION.
- 2. SIDE ROAD WITH A SPEED LIMIT GREATER THAN 40 MPH (60 km/h)
 AS SHOWN ON THE DRAWING AND AS DIRECTED BY THE ENGINEER:
- o) ONE ROAD CONSTRUCTION AHEAD SIGN 48 × 48 (1.2 m × 1.2 m) WITH A FLASHER MOUNTED ON IT APPROXIMATELY 500' (150 m) IN ADVANCE OF THE MAIN POLITY.
- b) THE CLOSED PORTION OF THE MAIN ROUTE SHALL BE PROTECTED BY BLOCKING WITH TYPE III BARRICADES, 1/2 OF THE CROSS SECTION OF THE CLOSED PORTION.
- 3. WHEN THE SIDE ROAD LIES BETWEEN THE BEGINNING OF THE MAINLINE SIGNING AND THE WORK ZONE, A SINGLE HEADED ARROW (MG-1) SHALL BE USED IN LIEU OF THE DOUBLE HEADED ARROW (MG-4).

- B. FOR A LANE CLOSURE ON A SIDE ROAD OR DRIVEWAY:
- USE APPLICABLE PORTIONS OF THE TYPICAL APPLICATION OF TRAFFIC CONTROL DEVICES (STD. 701501, STD. 701606 OR THE APPROPRIATE STANDARD). THE SPACING OF SIGNS AND BARRICADES SHALL BE ADJUSTED FOR FIELD CONDITIONS AS DIRECTED BY THE ENGINEER. THE DIRECTIONAL ARROW SHALL BE COVERED OR REMOYED WHEN NO LONGER CONSISTENT WITH THE SIDE ROAD LANE CLOSURE.
- C. ADVANCE WARNING SIGNS ARE TO BE OMITTED ON DRIVEWAY UNLESS OTHERWISE NOTED.
- D. THE TRAFFIC CONTROL AND PROTECTION FOR SIDE ROADS, INTERSECTIONS, AND DRIVEWAYS SHALL BE INCIDENTAL TO THE COST OF SPECIFIED TRAFFIC CONTROL STANDARDS OR ITEMS.

All dimensions are in millimeters (inches) unless otherwise shown,

COUNTY


CONTRACT NO.

TOTAL SHEE NO.

١	FILE NAME =	USER NAME = gaglianobt	DESIGNED - LHA	REVISED - J. OBERLE 10-18-95
	Wi\diststd\22x34\tcl0.dgn		DRAWN -	REVISED - A. HOUSEH 03-06-9
		PLOT SCALE = 50.000 '/ IN.	CHECKED -	REVISED - A. HOUSEH 10-15-96
1		PLOT DATE = 1/4/2008	DATE - 06-89	REVISED -T. RAMMACHER 01-06-


STATE OF ILLINOIS
DEPARTMENT OF TRANSPORTATION


TRAFFIC CONTROL AND PROTECTION FOR	F.A.P. RTE.	SECTION
SIDE ROADS, INTERSECTIONS, AND DRIVEWAYS	347	09-00248-00-R
		TC-10
CALE: NONE SHEET NO. 1 OF 1 SHEETS STA. TO STA.	FFD. R	DAD DIST NO 1 ILLINOIS




*** REDUCE TO 40' (12 m) O.C. ON CURVES WITH POSTED OR ADVISORY SPEED 45 M.P.H. (70 km/h) OR LESS.

TWO-LANE/TWO-WAY






TWO-WAY LEFT TURN



MULTI-LANE/UNDIVIDED



MULTI-LANE/DIVIDED

GENERAL NOTES

- MARKERS USED WITH DASHED LINES SHALL BE CENTERED IN THE GAP BETWEEN SEGMENTS.
- 2. MARKERS USED ADJACENT TO SOLID LINES SHALL BE OFFSET 2 TO 3 (50 TO 75) TOWARD TRAFFIC AS SHOWN.
- 3. MARKERS THROUGH TANGENTS LESS THAN 500' (150 m) IN LENGTH BETWEEN CURVES SHALL BE INSTALLED AT THE LESSER OF THE TWO CURVE SPACINGS.

LANE MARKER NOTES

- A. USE DOUBLE LANE LINE MARKERS SPACED AS SHOWN.
- B. REDUCE TO 40' (12 m) O.C. ON CURVES WHERE ADVISORY SPEEDS ARE 10 M.P.H.(20 km/h) LOWER THAN POSTED SPEEDS.

SYMBOLS

----- YELLOW STRIPE

WHITE STRIPE

- ONE-WAY AMBER MARKER
 ONE-WAY CRYSTAL MARKER (W/O)
- ◆ TWO-WAY AMBER MARKER

DESIGN NOTES


1. DOUBLE LANE LINE MARKERS SHALL BE USED UNLESS SPECIFIED OTHERWISE.


- 2. EXCEPT AS SHOWN ON THE LANE REDUCTION TRANSITION AND FREEWAY
 EXIT RAMP DETAIL, MARKERS ARE NOT TO BE SPECIFIED ON RIGHT EDGE
 LINES.
- THE EXACT MARKER LIMITS, SPACING, AND COLOR SHOULD BE INCLUDED IN THE PLANS.
- 4. MARKERS SHOULD NOT BE USED ALONGSIDE CURBS EXCEPT FOR EXTREMELY SHORT SECTIONS OF CURBS WHERE NOT MORE THAN TWO MARKERS WOULD BE INVOLVED.

LEFT TURN


All dimensions are in inches (millimeters) unless otherwise shown.

FILE NAME :	USER NAME = drivakosgn	DESIGNED -	REVISED -T. RAMMACHER 09-19-94		TYPICAL APPLICATIONS	F.A.P. SECTION	COUNTY TOTAL SHEET
c:\pw_work\pwidot\drivakosgn\d0108315\t	ol1.dgn	DRAWN -	REVISED -T. RAMMACHER 03-12-99	STATE OF ILLINOIS		347 09-00248-00-RS	SHEETS NO.
	PLOT SCALE = 50.000 '/ IN.	CHECKED ~	REVISED -T. RAMMACHER 01-06-00	DEPARTMENT OF TRANSPORTATION	RAISED REFLECTIVE PAVEMENT MARKERS (SNOW-PLOW RESISTANT)	TC-11	CONTRACT NO.
	PLOT DATE = 9/9/2009	DATE -	REVISED - C. JUCIUS 09-09-09		SCALE: NONE SHEET NO. 1 OF 1 SHEETS STA. TO STA.	FED. ROAD DIST, NO. 1 ILLINOIS FED. A	ID PROJECT






4' (1.2 m) WIDE MEDIANS ONLY




DIAGONAL LINE SPACING: 50' (15 m) C-C (LESS THAN 30MPH (50 km/h))
75' (25 m) C-C 30MPH (50 km/h) TO 45MPH (70 km/h))
150' (45 m) C-C (MORE THAN 45MPH (70 km/h))

MEDIANS OVER 4' (1.2 m) WIDE




A MINIMUM OF TWO PAIRS OF TURN ARROWS SHALL BE USED, WHITE IN COLOR. ADDITIONAL PAIRS SHALL BE PLACED AT 200' (60 m) TO 300' (90 m) INTERVALS.



MEDIAN WITH TWO-WAY LEFT TURN LANE

TYPICAL PAINTED MEDIAN MARKING




FULL SIZE LETTERS 8' (2.4 m) AND ARROWS SHALL BE USED. \P AREA = 15.6 SQ. FT. (1.5 m²) \P

★ TURN LANES IN EXCESS OF 400' (120 m) IN LENGTH MAY HAVE AN ADDITIONAL
SET OF ARROW - "ONLY" INSTALLED MIDWAY BETWEEN THE OTHER TWO SETS OF
ARROW - "ONLY".

TYPICAL LEFT (OR RIGHT) TURN LANE

TYPICAL TURN LANE MARKING



TYPICAL ISLAND MARKING

TYPE OF MARKING	WIDTH OF LINE	PATTERN	COLOR	SPACING / REMARKS
CENTERLINE ON 2 LANE PAVEMENT	4 (100)	SKIP-DASH	YELLOW	10' (3 m) LINE WITH 30' (9 m) SPACE
CENTERLINE ON MULTI-LANE UNDIVIDED PAVEMENT	2 @ 4 (100)	SOLID	YELLOW	11 (280) C-C
NO PASSING ZONE LINES: FOR ONE DIRECTION FOR BOTH DIRECTIONS	4 (100) 2 @ 4 (100)	SOLID SOLID	YELLOW YELLOW	5/2 (140) C-C FROM SKIP-DASH CENTERLINE 11 (280) C-C OMIT SKIP-DASH CENTERLINE BETWEEN
LANE LINES	4 (100) 5 (125) ON FREEWAYS	SKIP-DASH SKIP-DASH	WHITE WHITE	10' (3 m) LINE WITH 30' (9 m) SPACE
DOTTED LINES (EXTENSIONS OF CENTER, LANE OR TURN LANE MARKINGS)	SAME AS LINE BEING EXTENDED	SKIP-DASH	SAME AS LINE BEING EXTENDED	2' (600) LINE WITH 6' (1.8 m) SPACE
EDGE LINES	4 (100)	SOLID	YELLOW-LEFT WHITE-RIGHT	OUTLINE MOUNTABLE MEDIANS IN YELLOW: EDGE LINES ARE NOT USED NEXT TO BARRIER CURB
TURN LANE MARKINGS	6 (150) LINE; FULL SIZE LETTERS & SYMBOLS (8' (2.4m))	SOLID	WHITE	SEE TYPICAL TURN LANE MARKING DETAIL
TWO WAY LEFT TURN MARKING	2 @ 4 (100) EACH DIRECTION	SKIP-DASH AND SOLID	YELLOW	10' (3 m) LINE WITH 30' (9 m) SPACE FOR SKIP-DASH; 5½ (140) C-C BETWEEN SOLID LINE AND SKIP-DASH LINE
•	8' (2.4m) LEFT ARROW	IN PAIRS	WHITE	SEE TYPICAL TWO-WAY LEFT TURN MARKING DETAIL
CROSSWALK LINES (PEDESTRIAN) A. DIAGONALS (BIKE & EQUESTRIAN) B. LONGITUDINAL BARS (SCHOOL)	2 @ 6 (150) 12 (300) @ 45° 12 (300) @ 90°	SOLID SOLID SOLID	WHITE WHITE WHITE	NOT LESS THAN 6' (1.8 m) APART 2' (500) APART 2' (500) APART 5EE TYPICAL CROSSWALK MARKING DETAILS.
STOP LINES	24 (600)	SOLID	WHITE	PLACE 4' (1.2 m) IN ADVANCE OF AND PARALLEL TO CROSSWALK, IF PRESENT. OTHERWISE, PLACE AT DESIRED STOPPING POINT. PARALLEL TO CROSSROAD CENTERLINE, WHERE POSSIBLE
PAINTED MEDIANS	2 @ 4 (100) WITH 12 (300) DIAGONALS	SOLID	YELLOW: TWO WAY TRAFFIC	11 (280) C-C FOR THE DOUBLE LINE
	e 45° NO DIAGONALS USED FOR 4' (1.2 m) WIDE MEDIANS		WHITE: ONE WAY TRAFFIC	SEE TYPICAL PAINTED MEDIAN MARKING.
GORE MARKING AND CHANNELIZING LINES	8 (200) WITH 12 (300) DIAGONALS @ 45°	SOLID	WHITE	DIAGONALS: 15' (4.5 m) C-C (LESS THAN 30MPH (50 km/h)) 20' (6 m) C-C 30MPH (50 km/h) TO 45MPH (70 km/h)) 30' (9 m) C-C (OVER 45MPH (70 km/h))
RAILROAD CROSSING	24 (600) TRANSVERSE LINES: "RR" IS 6' (1.8 m) LETTERS; 16 (400) LINE FOR "X"	SOLID	WHITE	SEE STATE STANDARD 780001 AREA OF: "R":3.6 SO. FT. (0.33 m²) EACH "X":54.0 SQ. FT. (5.0 m²)
SHOULDER DIAGONALS	12 (300) @ 45°	SOLID	WHITE - RIGHT YELLOW - LEFT	50' (15 m) C-C (LESS THAN 30MPH (50 km/h)) : 75' (25 m) C-C (30 MPH (50 km/h) TO 45MPH (70 km/h) 1150' (45 m) C-C (0VER 45MPH (70 km/h))


FOR FURTHER DETAILS ON PAVEMENT MARKING REFER TO STANDARD SPECIFICATIONS FOR ROAD AND BRIDGE CONSTRUCTION AND STATE STANDARD 780001.


All dimensions are in inches (millimeters) unless otherwise shown.

FILE NAME =	USER NAME = drivakosgn	DESIGNED - E	EVERS	REVISED	-T. RAMMACHER	10-27-9
c:\pw_work\pwidot\drivakosgn\d0108315\tc	13.dgn	DRAWN -		REVISED	-C. JUCIUS	09-09-0
	PLOT SCALE = 50.000 '/ IN. 3	CHECKED -		REVISED	-	
<u></u>	PLOT DATE = 9/9/2009	DATE - C	03-19-90	REVISED	-	


STATE OF ILLINOIS
DEPARTMENT OF TRANSPORTATION

DISTRICT ONE	F.A.P. RTE.	SECTION	COUNTY	TOTAL SHEETS	SHEE NO.
TYPICAL PAVEMENT MARKINGS	347	09-00248-00-RS	COOK	274	272
COMP HOUSE CUSTS NO. 1 OF 1 CUSTS CALL		TC-13	CONTRACT	NO.	
SCALE: NONE SHEET NO. 1 OF 1 SHEETS STA. TO STA.	FED. RO	OAD DIST. NO. 1 ILLINOIS FED. AL	D PROJECT		






OUANTITY 4 (100) LINE = 45.5 ft. (13.9 m) 15.2 sq. ft. (1.39 sq. m)



QUANTITY 4 (100) LINE = 82.5 ft. (25.3 m) 27.5 sq. ft. (2.53 sq. m)

All dimensions are in inches (millimeters) unless otherwise shown.

FILE NAME =	USER NAME = gaglianobt	DESIGNED -	REVISED -T. RAMMACHER 06-05-96		PAVEME	NT MARKING LETTERS AND SYMBOLS	F.A.P.	SECTION	COUNTY	TOTAL SHEET
W:\diststd\22x34\ta16.dgn	PLOT SCALE = 50.0000 '/ IN.	DRAWN - CHECKED -	REVISED -T. RAMMACHER 11-04-97 REVISED -T. RAMMACHER 03-02-98	STATE OF ILLINOIS DEPARTMENT OF TRANSPORTATION		FOR TRAFFIC STAGING	347 09-00248-00-RS	COOK	274 273	
	PLOT DATE = 1/4/2008	DATE - 09-18-94	REVISED - E. GOMEZ 08-28-00		SCALE: NONE SHEET NO	. 1 OF 1 SHEETS STA. TO STA.	FED. ROAD D	TC-16	CONTRACT	NU ₄



NOTES:

- 1. USE BLACK LETTERING ON ORANGE BACKGROUND.
- 2. ERECT SIGNS IN ADVANCE OF THE LOCATION FOR THE "ROAD CONSTRUCTION AHEAD" SIGN AT LOCATIONS AS DIRECTED BY THE ENGINEER.
- 3. ERECT SIGN (1) WITH INSTALLED PANEL (2) ONE WEEK PRIOR TO THE START OF CONSTRUCTION.
- 4. REMOVE PANEL (2) SOON AFTER THE START OF CONSTRUCTION.
- 5. SEE SPECIAL PROVISION FOR "TEMPORARY INFORMATION SIGNING" FOR ADDITIONAL INFORMATION.
- 6. ONE SIGN ASSEMBLY EQUALS 25.70 SQ. FT. (2.3 SQ. M.)
- 7. SHALL BE PAID FOR AS TEMPORARY INFORMATION SIGNING.

ALL DIMENSIONS ARE IN INCHES (MILLIMETERS)
UNLESS OTHERWISE SHOWN.

FILE NAME =	USER NAME = geglianobt	DESIGNED -	REVISED - R. MIRS 09-15-97		ADTERIAL DOAD	F.A.P. SECTION COL	DUNTY TOTAL SHEET
Ws\diststd\22x34\tc22.dgn		DRAWN -	REVISED - R. MIRS 12-11-97	STATE OF ILLINOIS	ARTERIAL ROAD	247 00 00040 00 70	SHEETS NU.
	PLOT SCALE = 50.000 '/ IN.	CHECKED ~	REVISED - T. RAMMACHER 02-02-99	DEPARTMENT OF TRANSPORTATION	INFORMATION SIGN		NTRACT NO.
	PLOT DATE = 1/4/2008	DATE -	REVISED - C. JUCIUS 01-31-07		SCALE: NONE SHEET NO. 1 OF 1 SHEETS STA. TO STA.	FED. ROAD DIST. NO. 1 ILLINOIS FED. AID PROJE	